

ABNORMAL TEST RESULT

OF MODEL RMC15U-1/RMC15A-1

1. Did Cheese Cloth or Paper Glow?

No.

2. Did Ground Fuse Open?

No.

3. Dielectric breakdown?

No.

4. Other Results?

See the following pages .

(Abnormal Test Result: 6-1 ~ 6-10)

There was no emission of flame, molten metal, ignition of cheesecloth, dielectric breakdown, opening of the ground fuse, other indication of a shock or fire hazard.

8. Abnormal Test [アブノーマル試験] : Bull.1402C, cl 5.5

Rated Input Current: 0.51 , Rated Output Voltage: AVR1: 5V
AVR2: 12V
AVR3: -12V

No.	Component [部品番号]	S/C[短絡] or OPEN [開放]	Gnd Fuse Open [接地ヒューズ断]	Flame or Glowing [赤熱または 融解]	Input Curr- ent	Output Volta- ge	Comment [コメント]
1	C11	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Fil open Hi pot ok
2	C13	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Fil open Hi pot ok
3	C14	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0.347	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
4	C15	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0.185	AVR1: 3.82 AVR2: 9.09 AVR3: -8.90	Hi pot ok
5	C16	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0.350	AVR1: 5 AVR2: 12 AVR3: -12	Fil open Hi pot ok
6	C17	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0.165	AVR1: 1.06 AVR2: 0.8 AVR3: -2.6	Hi pot ok
7	C51	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0.036	AVR1: 0 AVR2: 0 AVR3: -0.2	Hi pot ok
8	C52	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0.036	AVR1: 0 AVR2: 0 AVR3: -0.2	Hi pot ok
9	C53	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0.036	AVR1: 0 AVR2: 0 AVR3: -0.2	Hi pot ok
10	C55	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0.209	AVR1: 3.58 AVR2: 9.77 AVR3: -9.9	Hi pot ok
11	C56	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0.005	AVR1: 0.1 AVR2: 0 AVR3: 0	Hi pot ok
12	C57	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0.005	AVR1: 0.1 AVR2: 0 AVR3: 0	Hi pot ok

Compliance [判定] : Yes [合] / No [否]

8. Abnormal Test [アブノーマル試験] : Bull.1402C,c1 5.5



Rated Input Current: 0.51 , Rated Output Voltage: AVR1:5V AVR2:12V AVR3:-12V

No.	Component [部品番号]	S/C[短絡] or OPEN [開放]	Gnd Fuse Open [接地ヒューズ断]	Flame or Glowing [赤熱または 融解]	Input Curr- ent	Output Volta- ge	Comment [コメント]
1	D58	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.102	AVR1: 1.37 AVR2: 0 AVR3: -3.5	Hi pot ok
2	D59	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.074	AVR1: 0.94 AVR2: 0.12 AVR3: 0	Hi pot ok
3	D11	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.047	AVR1: 1.17 AVR2: 0.4 AVR3: -3.0	Hi pot ok
4	D12	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.347	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change.
5	D13	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.008	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot ok
6	D14	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.185	AVR1: 3.32 AVR2: 2.09 AVR3: -9.4	Hi pot ok
7	D51	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.063	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot ok
8	D52	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.063	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot ok
9	D53	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.481	AVR1: 5.86 AVR2: 12 AVR3: -12	Hi pot ok
10	D54	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.065	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot ok
11	D55	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.065	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot ok
12	D56	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.102	AVR1: 1.36 AVR2: 0 AVR3: -3.5	Hi pot ok

Compliance [判定] : Yes [合] / No [否]

8. Abnormal Test [アブノーマル試験] : Bull.1402C, cl 5.5

Rated Input Current: 0.51, Rated Output Voltage: AVR1: 5V
AVR2: 12V
AVR3: -12V

No.	Component [部品番号]	S/C[短絡] or OPEN [開放]	Gnd Fuse Open [接地ヒューズ断]	Flame or Glowing [赤熱または 融解]	Input Curr- ent	Output Volta- ge	Comment [コメント]
1	D57	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0.074	AVR1: 0.94 AVR2: 0.18 AVR3: 0	Hi pot ok
2	IC51 (k-A)	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0.043	AVR1: 1.11 AVR2: 0.2 AVR3: -0.28	Hi pot ok
3	IC51 (k-R)	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0.177	AVR1: 3.22 AVR2: 2.77 AVR3: -9.1	Hi pot ok
4	IC51 (A-R)	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0.552	AVR1: 6.75 AVR2: 12 AVR3: -12	Hi pot ok
5	IC52 (I-D)	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0.400	AVR1: 5 AVR2: 15.7 AVR3: -12	Hi pot ok
6	IC52 (D-A)	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0.102	AVR1: 1.36 AVR2: 0 AVR3: -3.5	Hi pot ok
7	IC52 (A-I)	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0.035	AVR1: 0.1 AVR2: 0 AVR3: 0	Hi pot ok
8	IC53 (I-D)	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0.362	AVR1: 5 AVR2: 12 AVR3: -15.2	Hi pot ok
9	IC53 (D-A)	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0.074	AVR1: 0.94 AVR2: 0.18 AVR3: 0	Hi pot ok
10	IC53 (A-I)	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0.035	AVR1: 0.1 AVR2: 0 AVR3: 0	Hi pot ok
11	L11 	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Fill open Hi pot ok
12	L11 	S/C	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes [有] <input checked="" type="checkbox"/> No [無]	0.361	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change

Compliance [判定] : Yes [合] / No [否]

8. Abnormal Test [アブノーマル試験] : Bull.1402C, cl 5.5

AVR1: 5V

AVR2: 12V

Rated Input Current: 0.51, Rated Output Voltage: AVR3: -12V

No.	Component [部品番号]	S/C[短絡] or OPEN [開放]	Gnd Fuse Open [接地ヒューズ断]	Flame or Glowing [赤熱または 融融]	Input Curr- ent	Output Volta- ge	Comment [コメント]
1	L51	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.351	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
2	LE-51	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.351	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
3	PCII LED (A-K)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.546	AVR1: 6.6 AVR2: 12 AVR3: -12	Hipot ok
4	PCII detector (C-E)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.01	AVR1: 0 AVR2: 0 AVR3: 0	Hipot ok
5	SSII	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Fil open Hipot ok
6	TII (2-3)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.085	AVR1: 0 AVR2: 0 AVR3: 0	Hipot ok
7	TII (3-4)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Fil open Hipot ok
8	TII (4-5)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.058	AVR1: 0 AVR2: 0 AVR3: 0	Hipot ok
9	TII (6-7)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.088	AVR1: 0 AVR2: 0 AVR3: 0	Hipot ok
10	TII (7-8)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.353	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
11	TII (8-9)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.084	AVR1: 0 AVR2: 0 AVR3: 0	Hipot ok
12	TII (9-10)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.082	AVR1: 0 AVR2: 0 AVR3: 0	Hipot ok

Compliance [判定] : Yes [合] / No [否]

8. Abnormal Test [アブノーマル試験] : Bull.1402C, cl 5.5

AVR1 : 5V

AVR2 : 12V

Rated Input Current: 0.51 , Rated Output Voltage: AVR3:-12V

No.	Component [部品番号]	S/C[短絡] or OPEN [開放]	Gnd Fuse Open [接地ヒューズ断]	Flame or Glowing [赤熱または溶融]	Input Curr- ent	Output Volta- ge	Comment [コメント]
1	TR11 (C-E)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.008	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot ok
2	TR11 (C-B)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.008	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot ok
3	TR11 (B-E)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Flt open Hi pot ok
4	TR12 (C-E)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Flt open Hi pot ok
5	TR12 (C-B)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Flt open Hi pot ok
6	TR12 (B-E)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.008	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot ok
7	ZD11	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.354	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
8	ZD12	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.008	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot ok
9	ZD13	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.169	AVR1: 3.12 AVR2: 2.44 AVR3: -2.78	Hi pot ok
10	ZD11	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.036	AVR1: 0 AVR2: 0 AVR3: -0.2	Hi pot ok
11	ZD12	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.035	AVR1: 0.1 AVR2: 0 AVR3: 0	Hi pot ok
12		S/C	<input type="checkbox"/> Yes[有] <input type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input type="checkbox"/> No [無]		AVR1: AVR2: AVR3:	

Compliance [判定] : Yes [合] / No [否]

8. Abnormal Test [アブノーマル試験] : Bull.1402C, cl 5.5

Rated Input Current: 0.51 , Rated Output Voltage: AVR1: 5V AVR2: 12V AVR3: -12V

No.	Component [部品番号]	S/C[短絡] or OPEN [開放]	Gnd Fuse Open [接地ヒューズ断]	Flame or Glowing [赤熱または溶融]	Input Curr- ent	Output Volta- ge	Comment [コメント]
1	C11	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.347	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
2	C13	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.420	AVR1: 3.78 AVR2: 10.8 AVR3: -10.8	Hi pot ok
3	C14	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.415	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
4	C15	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.042	AVR1: 1.21 AVR2: 0.58 AVR3: 3.07	Hi pot ok
5	C16	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.347	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
6	C17	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.347	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
7	C51	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.347	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
8	C52	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.347	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
9	C53	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.347	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
10	C55	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.346	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
11	C56	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.344	AVR1: 5 AVR2: 11.9 AVR3: 12	Hi pot ok
12		open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]		AVR1: AVR2: AVR3:	

Compliance [判定] : Yes [合] / No [否]

8. Abnormal Test [アブノーマル試験] : Bull.1402C,cl 5.5

AVR1 : 5V

AVR2 : 12V

Rated Input Current: 0.51 , Rated Output Voltage: AVR3:-12V

No.	Component [部品番号]	S/C[短絡] or OPEN [開放]	Gnd Fuse Open [接地ヒューズ断]	Flame or Glowing [赤熱または溶融]	Input Curr- ent	Output Volta- ge	Comment [コメント]
1	C57	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.347	AVR1: 5V AVR2: 12V AVR3: -12V	Nothing change
2	C58	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.347	AVR1: 5V AVR2: 12V AVR3: -12V	Nothing change
3	C59	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.347	AVR1: 5V AVR2: 12V AVR3: -12V	Nothing change
4	D11	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.352	AVR1: 60V AVR2: 12V AVR3: -12V	Hi pot ok
5	D12	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.351	AVR1: 5V AVR2: 12V AVR3: -12V	Nothing change.
6	D13	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.347	AVR1: 5V AVR2: 12V AVR3: -12V	Nothing change
7	D14	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.347	AVR1: 5V AVR2: 12V AVR3: -12V	Nothing change
8	D51	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.350	AVR1: 5V AVR2: 12V AVR3: -12V	Nothing change
9	D52	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.350	AVR1: 5V AVR2: 12V AVR3: -12V	Nothing change
10	D53	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.347	AVR1: 5V AVR2: 12V AVR3: -12V	Nothing change
11	D54	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.266	AVR1: 5V AVR2: 0V AVR3: -12V	Hi pot ok
12	D55	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.294	AVR1: 5V AVR2: 12V AVR3: 0V	Hi pot ok

Compliance [判定] : Yes [合] / No [否]

8. Abnomal Test [アブノーマル試験] : Bull.1402C,cl 5.5

AVR1 : 5V
AVR2 : 12V

Rated Input Current: 0.51 , Rated Output Voltage: AVR3:-12V

No.	Component [部品番号]	S/C[短絡] or OPEN [開放]	Gnd Fuse Open -- [接地ヒューズ断]	Flame or Glowing [赤熱または溶融]	Input Curr- ent	Output Volta- ge	Comment [コメント]
1	D56	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.397	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
2	D57	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.397	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
3		open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]		AVR1: AVR2: AVR3:	
4	IC51 (K)	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.552	AVR1: 6.05 AVR2: 12 AVR3: -12	Hi pot ok
5	IC51 (A)	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.552	AVR1: 6.05 AVR2: 12 AVR3: -12	Hi pot ok
6	IC51 (R)	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.552	AVR1: 6.05 AVR2: 12 AVR3: -12	Hi pot ok
7	IC52 (I)	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.266	AVR1: 5 AVR2: 0 AVR3: -12	Hi pot ok
8	IC52 (O)	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.266	AVR1: 5 AVR2: 0 AVR3: -12	Hi pot ok
9	IC52 (G)	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.357	AVR1: 5 AVR2: 13.3 AVR3: -12	Hi pot ok
10	IC53 (I)	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.294	AVR1: 5 AVR2: 12 AVR3: 0	Hi pot ok
11	IC53 (O)	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.294	AVR1: 5 AVR2: 12 AVR3: 0	Hi pot ok
12	IC53 (G)	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.353	AVR1: 5 AVR2: 12 AVR3: -12	Hi pot ok

Compliance [判定] : Yes [合] / No [否]

8. Abnormal Test [アブノーマル試験] : Bull.1402C, cl 5.5

AVR1 : 5V

AVR2 : 12V

Rated Input Current: 0.51 , Rated Output Voltage: AVR3: -12V

No.	Component [部品番号]	S/C[短絡] or OPEN [開放]	Gnd Fuse Open [接地ヒューズ断]	Flame or Glowing [赤熱または溶融]	Input Curr- ent	Output Volta- ge	Comment [コメント]
1	L11	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hipot ok
2	L51	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.032	AVR1: 0 AVR2: 0 AVR3: 0	Hipot ok
3	LED51	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.347	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
4	PC11 LED (K,A)	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.552	AVR1: 6.75 AVR2: 12 AVR3: -12	Hipot ok
5	PC11 Detector (C,E)	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.552	AVR1: 6.75 AVR2: 12 AVR3: -12	Hipot ok
6	SS11	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hipot ok
7	T11 (3or2)	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.008	AVR1: 0 AVR2: 0 AVR3: 0	Hipot ok
8	T11 (4or5)	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.005	AVR1: 0 AVR2: 0 AVR3: 0	Hipot ok
9	T11 (6or7)	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.032	AVR1: 0 AVR2: 0 AVR3: 0	Hipot ok
10	T11 (8)	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.266	AVR1: 5 AVR2: 0 AVR3: -12	Hipot ok
11	T11 (9)	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.325	AVR1: 5 AVR2: 12 AVR3: -12	Hipot ok
12	T11 (10)	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.394	AVR1: 5 AVR2: 12 AVR3: 0	Hipot ok

Compliance [判定] : Yes [合] / No [否]

8. Abnormal Test [アブノーマル試験] : Bull.1402C,cl 5.5

AVR1: 5V
AVR2: 12V

Rated Input Current: 0.51 , Rated Output Voltage: AVR3: -12V

No.	Component [部品番号]	S/C[短絡] or OPEN [開放]	Gnd Fuse Open [接地ヒューズ断]	Flame or Glowing [赤熱または 融解]	Input Curr- ent	Output Volta- ge	Comment [コメント]
1	TH11	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hipot ok
2	TR11 (C.E.B)	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Fl open Hi pot ok
3	TR12 (C.E.B)	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.008	AVR1: 0 AVR2: 0 AVR3: 0	Hipot ok
4	ZD11	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.347	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change.
5	ZD12	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.347	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
6	ZD13	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.245	AVR1: 3.88 AVR2: 10.8 AVR3: -11.0	Hipot ok
7	ZD51	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.347	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
8	ZD52	open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.347	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
9		open	<input type="checkbox"/> Yes[有] <input type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input type="checkbox"/> No [無]		AVR1: AVR2: AVR3:	
10		open	<input type="checkbox"/> Yes[有] <input type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input type="checkbox"/> No [無]		AVR1: AVR2: AVR3:	
11		open	<input type="checkbox"/> Yes[有] <input type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input type="checkbox"/> No [無]		AVR1: AVR2: AVR3:	
12		open	<input type="checkbox"/> Yes[有] <input type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input type="checkbox"/> No [無]		AVR1: AVR2: AVR3:	

Compliance [判定] : Yes [合] / No [否]