

Approved : Takahiro Yoneda
Takahiro YonedaPrepared : Koji Todo
Koji Todo

No.	Test item	Conditions	Conditions of acceptability	Result
1	High temp./overload test	(1) Rated input (AC100V,200V) (2) Overload (3) Ambient temp. 50°C (4) Test period 48 hours	(1)Power supply is not failed.	ok
2	Capacitance reduction test	(1) Rated input (AC100V,200V) (2) Rated output (3) Ambient temp. 25±10°C	(1)No smoke, no fire. (2)No rise of the output voltage.	ok
3	Low voltage input test	(1) Input Min. regulation voltage (AC66V) (2) Rated output (3) Ambient temp. 25±10°C (4) Test period 48 hours	(1)Power supply is not failed.	ok
4	Input ON/OFF test	(1) Rated input (AC200V) T= 2sec Duty= 50% (2) Rated output (3) Ambient temp. 25±10°C	(1)Power supply is not failed. (2)The surge current of each components should not exceed the rated value.	ok
5	Output ON/OFF test	(1) Input Max.voltage (AC264V) (2) Output 0%←→100% T= 2sec Duty= 50% (3) Ambient temp. 25±10°C	(1)Power supply is not failed.	ok
6	Output-short start test	(1) Rated input (AC100V,200V) (2) Output Short start (3) Ambient temp. 25±10°C	(1)Power supply is not failed.	ok
7	Output short test	(1) Input AC264V (2) Output Short (3) Ambient temp. 25±10°C (4) Test period 48 hours	(1)Power supply is not failed.	ok
8	Withstand voltage test (High-pot test)	(1) Input Not applied. (2) Ambient temp. 25±10°C (3) The applied voltage is 1.4 times of specifications.	(1)Insulatin breakdown , flashover or electric arc is not occurred	ok
9	Isolation resistance test	(1) Input Not applied. (2) Ambient temp. 25±10°C	(1)When a regulation voltage is applied, isolation resistance is 1.4 times of specifications.	ok
10	Vibration/impact test	Vibration (1)f=10~150Hz : 19.6m/s ² (2)3 minutes period (3)60 minutes along X, Y and Z axis Impact (1)196.1m/s ² 11ms (2)Once each X, Y and Z axis	(1)No degradation of electric characteristics after test. (2)No crack at solder joint. (3)No marked damage of appearance.	ok
11	Line Noise Tolerance test	(1) Input AC230V (2) Rated Output (3) Ambient temp. 25±10°C (4) Test Voltage ±3 kV (5) Pulse width 50~1000nS (6) Mode Normal and Common	(1)No protection circuit failure. (2)No output voltage drop with control circuit failure. (3)No any other function failure	ok