

# TEST DATA OF CBS1002415

(24V INPUT)

Regulated DC Power Supply  
Jun. 22, 2002

Approved by : Isao Yasuda  
Isao Yasuda Design Manager

Prepared by : Kouichi Kinoshita  
Kouichi Kinoshita Design Engineer

**コーセル株式会社**  
**COSEL CO.,LTD.**

## C O N T E N T S

1.	Line Regulation . . . . .	1
	静的入力変動	
2.	Input Current (by Input Voltage) . . . . .	2
	入力電流 (入力電圧特性)	
3.	Input Current (by Load Current) . . . . .	3
	入力電流 (負荷特性)	
4.	Input Power (by Load Current) . . . . .	4
	入力電力 (負荷特性)	
5.	Efficiency (by Input Voltage) . . . . .	5
	効率 (入力電圧特性)	
6.	Efficiency (by Load Current) . . . . .	6
	効率 (負荷特性)	
7.	Load Regulation . . . . .	7
	静的負荷変動	
8.	Ripple Voltage (by Load Current) . . . . .	8
	リップル電圧 (負荷特性)	
9.	Ripple-Noise . . . . .	9
	リップルノイズ	
10.	Overcurrent Protection . . . . .	10
	過電流保護	
11.	Overvoltage Protection . . . . .	11
	過電圧保護	
12.	Dynamic Load Response . . . . .	12
	動的負荷変動	
13.	Rise and Fall Time . . . . .	13
	立上り、立下り時間	
14.	Ambient Temperature Drift . . . . .	14
	周囲温度変動	
15.	Minimum Input Voltage for Regulated Output Voltage . . . . .	15
	最低レギュレーション電圧	
16.	Ripple Voltage (by Ambient Temperature) . . . . .	16
	リップル電圧 (周囲温度特性)	
17.	Time Lapse Drift . . . . .	17
	経時ドリフト	
18.	Output Voltage Accuracy . . . . .	18
	定電圧精度	
19.	Condensation . . . . .	19
	結露特性	
20.	Line Noise Tolerance . . . . .	20
	入力雑音耐量	
21.	Figure of Testing Circuitry . . . . .	21
	測定回路図	

(Final Page 21)



<p>Model CBS1002415</p> <p>Item Line Regulation 静的入力変動</p> <p>Object +15V6.7A</p>		<p>Temperature 25°C</p> <p>Testing Circuitry Figure A</p>																																
<p>1. Graph</p> <div style="text-align: right;"> <p>---□--- Load 50%</p> <p>—△— Load 100%</p> </div> <p>Note: Slanted line shows the range of the rated input voltage.</p> <p>(注) 斜線は定格入力電圧範囲を示す。</p>		<p>2. Values</p> <table border="1"> <thead> <tr> <th rowspan="2">Input Voltage [V]</th> <th colspan="2">Output Voltage [V]</th> </tr> <tr> <th>Load 50%</th> <th>Load 100%</th> </tr> </thead> <tbody> <tr><td>16</td><td>14.952</td><td>14.953</td></tr> <tr><td>18</td><td>14.952</td><td>14.953</td></tr> <tr><td>20</td><td>14.952</td><td>14.953</td></tr> <tr><td>24</td><td>14.953</td><td>14.953</td></tr> <tr><td>30</td><td>14.953</td><td>14.952</td></tr> <tr><td>36</td><td>14.953</td><td>14.952</td></tr> <tr><td>40</td><td>14.953</td><td>14.952</td></tr> <tr><td>--</td><td>--</td><td>--</td></tr> <tr><td>--</td><td>--</td><td>--</td></tr> </tbody> </table>	Input Voltage [V]	Output Voltage [V]		Load 50%	Load 100%	16	14.952	14.953	18	14.952	14.953	20	14.952	14.953	24	14.953	14.953	30	14.953	14.952	36	14.953	14.952	40	14.953	14.952	--	--	--	--	--	--
Input Voltage [V]	Output Voltage [V]																																	
	Load 50%	Load 100%																																
16	14.952	14.953																																
18	14.952	14.953																																
20	14.952	14.953																																
24	14.953	14.953																																
30	14.953	14.952																																
36	14.953	14.952																																
40	14.953	14.952																																
--	--	--																																
--	--	--																																




Model	CBS1002415
Item	Input Current (by Input Voltage) 入力電流 (入力電圧特性)
Object	_____

Temperature 25°C  
Testing Circuitry Figure A

1. Graph

- △— Load 100%
- - -□- - - Load 50%
- · -○- · - Load 0%



Note: Slanted line shows the range of the rated input voltage.

(注) 斜線は定格入力電圧範囲を示す。

2. Values


Input Voltage [V]	Input Current [A]		
	Load 0%	Load 50%	Load 100%
0	0.000	0.000	0.000
4.0	0.000	0.000	0.000
8.0	0.000	0.000	0.000
12.0	0.016	0.016	0.016
15.6	0.119	3.634	7.400
16.0	0.117	3.540	7.260
18.0	0.109	3.150	6.400
20.0	0.094	2.824	5.740
24.0	0.078	2.372	4.740
28.0	0.070	2.046	4.082
32.0	0.065	1.801	3.576
36.0	0.060	1.611	3.180
40.0	0.057	1.467	2.876
--	--	--	--
--	--	--	--
--	--	--	--



Model	CBS1002415
Item	Input Current (by Load Current) 入力電流 (負荷特性)
Object	_____

Temperature 25°C  
Testing Circuitry Figure A

1. Graph  
 —△— Input Volt. 18V  
 - - □ - - Input Volt. 24V  
 - - ○ - - Input Volt. 36V



2. Values

Load Current [A]	Input Current [A]		
	Input Volt. 18[V]	Input Volt. 24[V]	Input Volt. 36[V]
0.00	0.109	0.078	0.059
1.00	1.032	0.791	0.561
2.00	1.938	1.460	1.010
3.00	2.880	2.150	1.458
4.00	3.856	2.854	1.918
5.00	4.870	3.581	2.384
6.00	5.940	4.332	2.863
6.70	6.720	4.870	3.204
7.37	7.480	5.400	3.536
--	--	--	--
--	--	--	--

Note: Slanted line shows the range of the rated load current.

(注) 斜線は定格負荷電流範囲を示す。




Model	CBS1002415
Item	Input Power (by Load Current) 入力電力 (負荷特性)
Object	_____

Temperature 25°C  
Testing Circuitry Figure A

1. Graph

- △— Input Volt. 18V
- Input Volt. 24V
- Input Volt. 36V



2. Values

Load Current [A]	Input Power [W]		
	Input Volt. 18[V]	Input Volt. 24[V]	Input Volt. 36[V]
0.00	2.0	1.9	2.1
1.00	18.4	18.9	20.2
2.00	34.3	34.7	36.3
3.00	50.5	50.9	52.3
4.00	67.1	67.4	68.8
5.00	84.4	84.1	85.3
6.00	102.0	101.3	102.1
6.70	114.6	113.7	114.1
7.37	126.9	125.6	125.9
--	--	--	--
--	--	--	--

Note: Slanted line shows the range of the rated load current.

(注) 斜線は定格負荷電流範囲を示す。




Model CBS1002415		Temperature 25°C																																
Item Efficiency (by Input Voltage) 効率 (入力電圧特性)		Testing Circuitry Figure A																																
Object _____																																		
<p>1. Graph</p> <p style="text-align: right;">             ---□--- Load 50%              —△— Load 100%         </p> <p style="text-align: center;">Input Voltage [V]</p>		<p>2. Values</p> <table border="1"> <thead> <tr> <th rowspan="2">Input Voltage [V]</th> <th colspan="2">Efficiency [%]</th> </tr> <tr> <th>Load 50%</th> <th>Load 100%</th> </tr> </thead> <tbody> <tr><td>16</td><td>88.4</td><td>86.7</td></tr> <tr><td>18</td><td>88.6</td><td>87.3</td></tr> <tr><td>20</td><td>88.6</td><td>87.6</td></tr> <tr><td>24</td><td>88.1</td><td>87.8</td></tr> <tr><td>30</td><td>87.0</td><td>87.9</td></tr> <tr><td>36</td><td>86.1</td><td>87.4</td></tr> <tr><td>40</td><td>85.2</td><td>87.2</td></tr> <tr><td>--</td><td>--</td><td>--</td></tr> <tr><td>--</td><td>--</td><td>--</td></tr> </tbody> </table>	Input Voltage [V]	Efficiency [%]		Load 50%	Load 100%	16	88.4	86.7	18	88.6	87.3	20	88.6	87.6	24	88.1	87.8	30	87.0	87.9	36	86.1	87.4	40	85.2	87.2	--	--	--	--	--	--
Input Voltage [V]	Efficiency [%]																																	
	Load 50%	Load 100%																																
16	88.4	86.7																																
18	88.6	87.3																																
20	88.6	87.6																																
24	88.1	87.8																																
30	87.0	87.9																																
36	86.1	87.4																																
40	85.2	87.2																																
--	--	--																																
--	--	--																																
<p>Note: Slanted line shows the range of the rated input voltage.</p> <p>(注) 斜線は定格入力電圧範囲を示す。</p>																																		



Model	CBS1002415
Item	Efficiency (by Load Current) 効率 (負荷特性)
Object	_____

Temperature	25°C
Testing Circuitry	Figure A

1. Graph
- △— Input Volt. 18V
  - - -□- - - Input Volt. 24V
  - - -○- - - Input Volt. 36V



2. Values

Load Current [A]	Efficiency [%]		
	Input Volt. 18[V]	Input Volt. 24[V]	Input Volt. 36[V]
0.00	—	—	—
1.00	80.8	78.6	73.5
2.00	86.7	85.7	81.9
3.00	88.5	87.8	85.4
4.00	88.8	88.4	86.6
5.00	88.2	88.5	87.3
6.00	87.7	88.2	87.6
6.70	87.1	87.8	87.5
7.37	86.5	87.4	87.2
--	—	—	—
--	—	—	—

Note: Slanted line shows the range of the rated load current.


(注) 斜線は定格負荷電流範囲を示す。



Model	CBS1002415
Item	Load Regulation 静的負荷変動
Object	+15V6.7A

Temperature 25°C  
Testing Circuitry Figure A

1. Graph
- △— Input Volt. 18V
  - - -□- - - Input Volt. 24V
  - · -○- · - Input Volt. 36V



2. Values

Load Current [A]	Output Voltage [V]		
	Input Volt. 18[V]	Input Volt. 24[V]	Input Volt. 36[V]
0.00	14.952	14.952	14.952
1.00	14.952	14.952	14.952
2.00	14.952	14.952	14.952
3.00	14.952	14.952	14.952
4.00	14.952	14.952	14.952
5.00	14.952	14.952	14.952
6.00	14.952	14.952	14.952
6.70	14.952	14.952	14.952
7.37	14.952	14.952	14.952
--	--	--	--

Note: Slanted line shows the range of the rated load current.


(注) 斜線は定格負荷電流範囲を示す。



Model	CBS1002415
Item	Ripple Voltage (by Load Current) リップル電圧 (負荷特性)
Object	+15V6.7A

Temperature 25°C  
Testing Circuitry Figure A

1. Graph



2. Values

Load Current [A]	Ripple Voltage [mV]	
	Input Volt. 18 [V]	Input Volt. 36 [V]
0.0	5	5
1.3	5	10
2.7	5	10
4.0	5	10
5.4	5	10
6.7	10	10
8.0	10	10
--	--	--
--	--	--
--	--	--
--	--	--

Ripple Voltage is shown as p-p in the figure below.

Note: Slanted line shows the range of the rated load current.

リップル電圧は、下図 p-p 値で示される。  
(注) 斜線は定格負荷電流範囲を示す。

Ripple [mVp-p]




Fig. Complex Ripple Wave Form  
図 リップル波形詳細図



<p>Model CBS1002415</p> <p>Item Ripple-Noise リップルノイズ</p> <p>Object +15V6.7A</p>		<p>Temperature 25°C</p> <p>Testing Circuitry Figure A</p>																																						
<p>1. Graph</p> <p>—△— Input Volt. 18V</p> <p>-·-○-·- Input Volt. 36V</p> <p>Ripple-Noise is shown as p-p in the figure below. Note: Slanted line shows the range of the rated load current.</p> <p>リップルノイズは、下図 p-p 値で示される。 (注) 斜線は定格負荷電流範囲を示す。</p> <p>Fig. Complex Ripple Noise Wave Form 図 リップルノイズ波形</p>		<p>2. Values</p> <table border="1"> <thead> <tr> <th rowspan="2">Load Current [A]</th> <th colspan="2">Ripple-Noise [mV]</th> </tr> <tr> <th>Input Volt. 18 [V]</th> <th>Input Volt. 36 [V]</th> </tr> </thead> <tbody> <tr><td>0.0</td><td>10</td><td>15</td></tr> <tr><td>1.3</td><td>15</td><td>20</td></tr> <tr><td>2.7</td><td>15</td><td>20</td></tr> <tr><td>4.0</td><td>20</td><td>25</td></tr> <tr><td>5.4</td><td>25</td><td>25</td></tr> <tr><td>6.7</td><td>30</td><td>30</td></tr> <tr><td>8.0</td><td>35</td><td>30</td></tr> <tr><td>--</td><td>--</td><td>--</td></tr> <tr><td>--</td><td>--</td><td>--</td></tr> <tr><td>--</td><td>--</td><td>--</td></tr> <tr><td>--</td><td>--</td><td>--</td></tr> </tbody> </table>	Load Current [A]	Ripple-Noise [mV]		Input Volt. 18 [V]	Input Volt. 36 [V]	0.0	10	15	1.3	15	20	2.7	15	20	4.0	20	25	5.4	25	25	6.7	30	30	8.0	35	30	--	--	--	--	--	--	--	--	--	--	--	--
Load Current [A]	Ripple-Noise [mV]																																							
	Input Volt. 18 [V]	Input Volt. 36 [V]																																						
0.0	10	15																																						
1.3	15	20																																						
2.7	15	20																																						
4.0	20	25																																						
5.4	25	25																																						
6.7	30	30																																						
8.0	35	30																																						
--	--	--																																						
--	--	--																																						
--	--	--																																						
--	--	--																																						

# COSEL


<p>Model CBS1002415</p> <p>Item Overcurrent Protection 過電流保護</p> <p>Object +15V6.7A</p>		<p>Temperature 25°C</p> <p>Testing Circuitry Figure A</p>																																																											
<p>1. Graph</p> <p>— Input Volt. 18V</p> <p>--- Input Volt. 24V</p> <p>..... Input Volt. 36V</p> <p>Output Voltage [V]</p> <p>Load Current [A]</p> <p>Note: Slanted line shows the range of the rated load current. (注) 斜線は定格負荷電流範囲を示す。</p> <p>Intermittent operation occurs when the output voltage is from 10.5V to 0V. 10.5V~0V間は、間欠モードとなる。</p>		<p>2. Values</p> <table border="1"> <thead> <tr> <th rowspan="2">Output Voltage [V]</th> <th colspan="3">Load Current [A]</th> </tr> <tr> <th>Input Volt. 18[V]</th> <th>Input Volt. 24[V]</th> <th>Input Volt. 36[V]</th> </tr> </thead> <tbody> <tr><td>15.00</td><td>6.72</td><td>6.73</td><td>6.86</td></tr> <tr><td>14.25</td><td>8.58</td><td>8.55</td><td>8.72</td></tr> <tr><td>13.50</td><td>8.58</td><td>8.58</td><td>8.77</td></tr> <tr><td>12.00</td><td>8.61</td><td>8.64</td><td>8.86</td></tr> <tr><td>10.50</td><td>8.62</td><td>8.67</td><td>8.96</td></tr> <tr><td>--</td><td>--</td><td>--</td><td>--</td></tr> <tr><td>--</td><td>--</td><td>--</td><td>--</td></tr> <tr><td>--</td><td>--</td><td>--</td><td>--</td></tr> <tr><td>--</td><td>--</td><td>--</td><td>--</td></tr> <tr><td>--</td><td>--</td><td>--</td><td>--</td></tr> <tr><td>--</td><td>--</td><td>--</td><td>--</td></tr> <tr><td>--</td><td>--</td><td>--</td><td>--</td></tr> <tr><td>--</td><td>--</td><td>--</td><td>--</td></tr> </tbody> </table>	Output Voltage [V]	Load Current [A]			Input Volt. 18[V]	Input Volt. 24[V]	Input Volt. 36[V]	15.00	6.72	6.73	6.86	14.25	8.58	8.55	8.72	13.50	8.58	8.58	8.77	12.00	8.61	8.64	8.86	10.50	8.62	8.67	8.96	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--
Output Voltage [V]	Load Current [A]																																																												
	Input Volt. 18[V]	Input Volt. 24[V]	Input Volt. 36[V]																																																										
15.00	6.72	6.73	6.86																																																										
14.25	8.58	8.55	8.72																																																										
13.50	8.58	8.58	8.77																																																										
12.00	8.61	8.64	8.86																																																										
10.50	8.62	8.67	8.96																																																										
--	--	--	--																																																										
--	--	--	--																																																										
--	--	--	--																																																										
--	--	--	--																																																										
--	--	--	--																																																										
--	--	--	--																																																										
--	--	--	--																																																										
--	--	--	--																																																										



Model	CBS1002415
Item	Overvoltage Protection 過電圧保護
Object	+15V6.7A

Testing Circuitry Figure A

1. Graph
- △— Input Volt. 18V
  - Input Volt. 24V
  - Input Volt. 36V



2. Values

Ambient Temperature [°C]	Operating Point [V]		
	Input Volt. 18[V]	Input Volt. 24[V]	Input Volt. 36[V]
-50	19.67	19.67	19.67
-40	19.67	19.67	19.67
-20	19.73	19.72	19.72
0	19.72	19.72	19.72
25	19.72	19.72	19.72
40	19.72	19.72	19.72
60	19.72	19.72	19.72
85	19.72	19.72	19.72
100	19.65	19.65	19.65
105	19.65	19.65	19.65
--	—	—	—

Note: Slanted line shows the range of the rated ambient temperature.

(注) 斜線は定格周囲温度範囲を示す。



Model	CBS1002415	Temperature	25°C
Item	Dynamic Load Response 動的負荷変動	Testing Circuitry	Figure A
Object	+15V6.7A		

Input Volt. 24 V  
Cycle 1000 ms


Load Current




Min. Load (0A) ←→

Load 100% (6.7A)

500 mV/div



500 μs/div




5 ms/div


Min. Load (0A) ←→

Load 50% (3.35A)

500 mV/div



500 μs/div




5 ms/div


Load 10% (0.67A) ←→

Load 100% (6.7A)

500 mV/div



500 μs/div




5 ms/div




Model	CBS1002415	Temperature	25°C
Item	Rise and Fall Time 立上り、立下り時間	Testing Circuitry	Figure A
Object	+15V6.7A		

1. Graph



2. Values

Load	Time	[mS]				
		T d	T r	T s	T h	T f
50 %		15.8	3.3	19.0	0.3	6.8
100 %		15.8	3.3	19.0	0.2	3.4






Model	CBS1002415
Item	Ambient Temperature Drift 周囲温度変動
Object	+15V6.7A

Testing Circuitry Figure A

1. Graph
- △— Input Volt. 18V
  - Input Volt. 24V
  - Input Volt. 36V



Note: Slanted line shows the range of the rated ambient temperature.

(注) 斜線は定格周囲温度範囲を示す。

2. Values


Ambient Temperature [°C]	Output Voltage [V]		
	Input Volt. 18[V]	Input Volt. 24[V]	Input Volt. 36[V]
-50	14.962	14.962	14.962
-40	14.965	14.965	14.965
-20	14.969	14.969	14.969
0	14.972	14.972	14.972
25	14.967	14.967	14.967
40	14.956	14.956	14.956
60	14.937	14.936	14.936
85	14.907	14.907	14.906
100	14.887	14.886	14.886
105	14.879	14.878	14.878
--	—	—	—



Model	CBS1002415
Item	Minimum Input Voltage for Regulated Output Voltage 最低レギュレーション電圧
Object	+15V6.7A

Testing Circuitry Figure A

1. Graph



Note: Slanted line shows the range of the rated ambient temperature.

(注) 斜線は定格周囲温度範囲を示す。

2. Values


Ambient Temperature [°C]	Input Voltage [V]	
	Load 50%	Load 100%
-50	12.8	13.3
-40	12.7	13.3
-20	12.9	13.5
0	12.9	13.6
25	13.0	13.7
40	13.0	13.8
60	13.1	13.8
85	13.1	13.9
100	13.1	13.9
105	13.1	13.9
--	--	--



Model	CBS1002415
Item	Ripple Voltage (by Ambient Temp.) リップル電圧 (周囲温度特性)
Object	+15V6.7A

Testing Circuitry Figure A

1. Graph



2. Values

Ambient Temperature [°C]	Ripple Voltage [mV]	
	Load 50%	Load 100%
-50	55	55
-40	55	55
-20	40	40
0	20	20
25	15	15
40	10	10
60	10	10
85	10	10
100	15	15
105	20	20
--	—	—

Note: Slanted line shows the range of the rated ambient temperature.

(注) 斜線は定格周囲温度範囲を示す。



<b>COSEL</b>																									
Model	CBS1002415	Temperature	25°C																						
Item	Time Lapse Drift 経時ドリフト	Testing Circuitry	Figure A																						
Object	+15V6.7A																								
1. Graph		2. Values																							
<p style="text-align: center;">Time [H]</p> <p>Input Volt.    24V Load            100%</p>		<table border="1"> <thead> <tr> <th>Time since start [H]</th> <th>Output Voltage [V]</th> </tr> </thead> <tbody> <tr><td>0.0</td><td>14.959</td></tr> <tr><td>0.5</td><td>14.952</td></tr> <tr><td>1.0</td><td>14.952</td></tr> <tr><td>2.0</td><td>14.952</td></tr> <tr><td>3.0</td><td>14.952</td></tr> <tr><td>4.0</td><td>14.952</td></tr> <tr><td>5.0</td><td>14.952</td></tr> <tr><td>6.0</td><td>14.952</td></tr> <tr><td>7.0</td><td>14.952</td></tr> <tr><td>8.0</td><td>14.952</td></tr> </tbody> </table>		Time since start [H]	Output Voltage [V]	0.0	14.959	0.5	14.952	1.0	14.952	2.0	14.952	3.0	14.952	4.0	14.952	5.0	14.952	6.0	14.952	7.0	14.952	8.0	14.952
Time since start [H]	Output Voltage [V]																								
0.0	14.959																								
0.5	14.952																								
1.0	14.952																								
2.0	14.952																								
3.0	14.952																								
4.0	14.952																								
5.0	14.952																								
6.0	14.952																								
7.0	14.952																								
8.0	14.952																								



		Testing Circuitry Figure A
Model	CBS1002415	
Item	Output Voltage Accuracy 定電圧精度	
Object	+15V6.7A	

1. Output Voltage Accuracy

This is defined as the value of the output voltage, regulation load, ambient temperature and input voltage varied at random in the range as specified below.

Temperature : -40 ~ 100°C

Input Voltage : 18 ~ 36V

Load Current : 0 ~ 6.7A

\* Output Voltage Accuracy =  $\pm(\text{Maximum of Output Voltage} - \text{Minimum of Output Voltage}) / 2$

\* Output Voltage Accuracy (Ration) =  $\frac{\text{Output Voltage}}{\text{Rated Output Voltage}} \times 100$

1. 定電圧精度

周囲温度、入力電圧、負荷電流を下記仕様内で、任意に変動させたときの出力電圧の変動をいう。

周囲温度 : -40 ~ 100°C

入力電圧 : 18 ~ 36V

負荷電流 : 0 ~ 6.7A

\* 定電圧精度(変動値) =  $\pm(\text{出力電圧の最高値} - \text{出力電圧の最低値}) / 2$

\* 定電圧精度(変動率) =  $\frac{\text{変動値}}{\text{定格出力電圧}} \times 100$

2. Values

Item	Temperature [°C]	Input Voltage[V]	Output		Output Voltage Accuracy	
			Current[A]	Voltage[V]	Value [mV]	Ration [%]
Maximum Voltage	25	18	0	14.966	±41	±0.3
Minimum Voltage	100	36	6.7	14.884		

# COSEL

Model		CBS1002415	Testing Circuitry Figure A
Item		Condense 結露特性	
Object		+15V6.7A	

## 1. Condensation test

Testing procedure is as follows.

- ① Keeping and cooling the unit in a tank at  $-10^{\circ}\text{C}$  for an hour with the input off.
- ② Taking it out of the tank and dewing itself in a room where the temperature is  $25^{\circ}\text{C}$  and the humidity is 40%RH.
- ③ Testing electrical characteristics of the unit to confirm there be no fault.

## 1. 結露特性試験

入力を切った状態で、恒温槽で $-10^{\circ}\text{C}$ に冷却しておき、約1時間後に恒温槽から取り出し、室温 $25^{\circ}\text{C}$ 、湿度40%RHの状態におき結露させ、その電気的特性の測定を行い異常のないことを確認する。

## 2. Values

Item	Data	Testing Conditions
Output Voltage [V]	15.040	Input Volt. :24V, Load Current. :6.7A
Line Regulation [mV]	3	Input Volt. :18~36V, Load Current. :6.7A
Load Regulation [mV]	1	Input Volt. :24V, Load Current. :0~6.7A



Model		CBS1002415	Temperature 25°C Testing Circuitry Figure B
Item		Line Noise Tolerance 入力雑音耐量	
Object		+15V6.7A	

1. Conditions

- Input Voltage : 24 V
- Pulse Voltage : 2000 V
- Pulse Cycle : 16.7 mS
- Pulse Input Duration : 1 min. or more
- Load : 100 %

2. Results

Pulse Width [nS]	MODE		No protection failure should occur	DC-like Regulation of Output Voltage
	POLARITY		保護回路の誤動作がない	出力電圧の直流的変動
50	COMMON	+	OK	no fluctuation
		-	OK	no fluctuation
	NORMAL	+	OK	no fluctuation
		-	OK	no fluctuation
1000	COMMON	+	OK	no fluctuation
		-	OK	no fluctuation
	NORMAL	+	OK	no fluctuation
		-	OK	no fluctuation




Figure A





Figure B



- C1 : 50V 68  $\mu$ F
- C2 : 4700pF
- C3 : 50V 0.1  $\mu$ F
- C4 : 25V 470  $\mu$ F  $\times$  2  $(-40^{\circ}\text{C} \leq T_B \leq -20^{\circ}\text{C})$   
 25V 470  $\mu$ F  $(-20^{\circ}\text{C} < T_B \leq 100^{\circ}\text{C})$
- $T_B$  : Base Plate Temp.

Figure C