



TEST DATA OF CBS1002424

(24V INPUT)

Regulated DC Power Supply
Jun. 20, 2002

Approved by : Isao Yasuda
Isao Yasuda Design Manager

Prepared by : Kouichi Kinoshita
Kouichi Kinoshita Design Engineer


コーセル株式会社
COSEL CO.,LTD.

CONTENTS

1. Line Regulation	1
静的入力変動	
2. Input Current (by Input Voltage)	2
入力電流 (入力電圧特性)	
3. Input Current (by Load Current)	3
入力電流 (負荷特性)	
4. Input Power (by Load Current)	4
入力電力 (負荷特性)	
5. Efficiency (by Input Voltage)	5
効率 (入力電圧特性)	
6. Efficiency (by Load Current)	6
効率 (負荷特性)	
7. Load Regulation	7
静的負荷変動	
8. Ripple Voltage (by Load Current)	8
リップル電圧 (負荷特性)	
9. Ripple-Noise	9
リップルノイズ	
10. Overcurrent Protection	10
過電流保護	
11. Overvoltage Protection	11
過電圧保護	
12. Dynamic Load Response	12
動的負荷変動	
13. Rise and Fall Time	13
立上り、立下り時間	
14. Ambient Temperature Drift	14
周囲温度変動	
15. Minimum Input Voltage for Regulated Output Voltage	15
最低レギュレーション電圧	
16. Ripple Voltage (by Ambient Temperature)	16
リップル電圧 (周囲温度特性)	
17. Time Lapse Drift	17
経時ドリフト	
18. Output Voltage Accuracy	18
定電圧精度	
19. Condensation	19
結露特性	
20. Line Noise Tolerance	20
入力雑音耐量	
21. Figure of Testing Circuitry	21
測定回路図	

(Final Page 21)

COSEL

Model	CBS1002424																																		
Item	Line Regulation 静的入力変動	Temperature	25℃																																
Object	+24V4.2A	Testing Circuitry	Figure A																																
1. Graph		2. Values																																	
<div><div><div>---</div><div>□</div><div>---</div></div><div>Load 50%</div></div> <div><div>—</div><div>△</div><div>—</div></div> <div>Load 100%</div> <div></div> <div>Note: Slanted line shows the range of the rated input voltage.</div> <div>(注) 斜線は定格入力電圧範囲を示す。</div>		<table><tr><th rowspan="2">Input Voltage [V]</th><th colspan="2">Output Voltage [V]</th></tr><tr><th>Load 50%</th><th>Load 100%</th></tr><tr><td>16</td><td>23.892</td><td>23.893</td></tr><tr><td>18</td><td>23.893</td><td>23.894</td></tr><tr><td>20</td><td>23.893</td><td>23.893</td></tr><tr><td>24</td><td>23.893</td><td>23.893</td></tr><tr><td>30</td><td>23.893</td><td>23.893</td></tr><tr><td>36</td><td>23.893</td><td>23.893</td></tr><tr><td>40</td><td>23.893</td><td>23.893</td></tr><tr><td>--</td><td>—</td><td>—</td></tr><tr><td>--</td><td>—</td><td>—</td></tr></table>		Input Voltage [V]	Output Voltage [V]		Load 50%	Load 100%	16	23.892	23.893	18	23.893	23.894	20	23.893	23.893	24	23.893	23.893	30	23.893	23.893	36	23.893	23.893	40	23.893	23.893	--	—	—	--	—	—
Input Voltage [V]	Output Voltage [V]																																		
	Load 50%	Load 100%																																	
16	23.892	23.893																																	
18	23.893	23.894																																	
20	23.893	23.893																																	
24	23.893	23.893																																	
30	23.893	23.893																																	
36	23.893	23.893																																	
40	23.893	23.893																																	
--	—	—																																	
--	—	—																																	

COSEL

Model		CBS1002424																																																																								
Item	Input Current (by Input Voltage) 入力電流 (入力電圧特性)																																																																									
Object																																																																										
1. Graph		2. Values																																																																								
<div><div><div>—△— Load 100%</div><div>---□--- Load 50%</div><div>---○--- Load 0%</div></div><table><thead><tr><th rowspan="2">Input Voltage [V]</th><th colspan="3">Input Current [A]</th></tr><tr><th>Load 0%</th><th>Load 50%</th><th>Load 100%</th></tr></thead><tbody><tr><td>0</td><td>0.000</td><td>0.000</td><td>0.000</td></tr><tr><td>4.0</td><td>0.000</td><td>0.000</td><td>0.000</td></tr><tr><td>8.0</td><td>0.000</td><td>0.000</td><td>0.000</td></tr><tr><td>12.0</td><td>0.016</td><td>0.015</td><td>0.016</td></tr><tr><td>15.6</td><td>0.127</td><td>3.700</td><td>7.510</td></tr><tr><td>16.0</td><td>0.124</td><td>3.614</td><td>7.310</td></tr><tr><td>18.0</td><td>0.104</td><td>3.188</td><td>6.450</td></tr><tr><td>20.0</td><td>0.096</td><td>2.857</td><td>5.800</td></tr><tr><td>24.0</td><td>0.083</td><td>2.398</td><td>4.850</td></tr><tr><td>28.0</td><td>0.076</td><td>2.068</td><td>4.145</td></tr><tr><td>32.0</td><td>0.071</td><td>1.823</td><td>3.638</td></tr><tr><td>36.0</td><td>0.067</td><td>1.632</td><td>3.260</td></tr><tr><td>40.0</td><td>0.063</td><td>1.483</td><td>2.952</td></tr><tr><td>--</td><td>--</td><td>--</td><td>--</td></tr><tr><td>--</td><td>--</td><td>--</td><td>--</td></tr><tr><td>--</td><td>--</td><td>--</td><td>--</td></tr></tbody></table></div> <div><p>Note: Slanted line shows the range of the rated input voltage.</p><p>(注) 斜線は定格入力電圧範囲を示す。</p></div>				Input Voltage [V]	Input Current [A]			Load 0%	Load 50%	Load 100%	0	0.000	0.000	0.000	4.0	0.000	0.000	0.000	8.0	0.000	0.000	0.000	12.0	0.016	0.015	0.016	15.6	0.127	3.700	7.510	16.0	0.124	3.614	7.310	18.0	0.104	3.188	6.450	20.0	0.096	2.857	5.800	24.0	0.083	2.398	4.850	28.0	0.076	2.068	4.145	32.0	0.071	1.823	3.638	36.0	0.067	1.632	3.260	40.0	0.063	1.483	2.952	--	--	--	--	--	--	--	--	--	--	--	--
Input Voltage [V]	Input Current [A]																																																																									
	Load 0%	Load 50%	Load 100%																																																																							
0	0.000	0.000	0.000																																																																							
4.0	0.000	0.000	0.000																																																																							
8.0	0.000	0.000	0.000																																																																							
12.0	0.016	0.015	0.016																																																																							
15.6	0.127	3.700	7.510																																																																							
16.0	0.124	3.614	7.310																																																																							
18.0	0.104	3.188	6.450																																																																							
20.0	0.096	2.857	5.800																																																																							
24.0	0.083	2.398	4.850																																																																							
28.0	0.076	2.068	4.145																																																																							
32.0	0.071	1.823	3.638																																																																							
36.0	0.067	1.632	3.260																																																																							
40.0	0.063	1.483	2.952																																																																							
--	--	--	--																																																																							
--	--	--	--																																																																							
--	--	--	--																																																																							

COSEL

Model		CBS1002424	
Item	Input Current (by Load Current) 入力電流 (負荷特性)		
Object			

1. Graph

—△—

Input Volt. 18V

---□---

Input Volt. 24V

---○---

Input Volt. 36V

Input Current [A]

10

8

6

4

2

0

0.0

1.0

2.0

3.0

4.0

5.0

Load Current [A]

Note: Slanted line shows the range of the rated load current.

(注) 斜線は定格負荷電流範囲を示す。

2. Values

Load Current [A]	Input Current [A]		
	Input Volt. 18[V]	Input Volt. 24[V]	Input Volt. 36[V]
0.00	0.102	0.081	0.066
0.80	1.295	0.984	0.695
1.60	2.493	1.862	1.275
2.40	3.744	2.778	1.866
3.20	5.040	3.710	2.480
4.00	6.410	4.680	3.116
4.20	6.760	4.930	3.274
4.62	7.520	5.460	3.612
--	--	--	--
--	--	--	--
--	--	--	--

COSEL

Model		CBS1002424		Temperature		25℃																																																				
Item		Input Power (by Load Current) 入力電力 (負荷特性)		Testing Circuitry		Figure A																																																				
Object		_____																																																								
1. Graph				2. Values																																																						
<div><div><div>—△—</div><div>Input Volt. 18V</div></div><div><div>---□---</div><div>Input Volt. 24V</div></div><div><div>---○---</div><div>Input Volt. 36V</div></div></div> <div>Input Power [W]</div> <div>Load Current [A]</div>				<table><tr><th rowspan="2">Load Current [A]</th><th colspan="3">Input Power [W]</th></tr><tr><th>Input Volt. 18[V]</th><th>Input Volt. 24[V]</th><th>Input Volt. 36[V]</th></tr><tr><td>0.00</td><td>1.8</td><td>1.9</td><td>2.4</td></tr><tr><td>0.80</td><td>23.0</td><td>23.5</td><td>25.0</td></tr><tr><td>1.60</td><td>44.0</td><td>44.2</td><td>45.8</td></tr><tr><td>2.40</td><td>65.3</td><td>65.6</td><td>67.0</td></tr><tr><td>3.20</td><td>87.3</td><td>87.2</td><td>88.7</td></tr><tr><td>4.00</td><td>109.9</td><td>109.5</td><td>111.2</td></tr><tr><td>4.20</td><td>115.6</td><td>115.1</td><td>116.7</td></tr><tr><td>4.62</td><td>127.9</td><td>127.1</td><td>128.6</td></tr><tr><td>--</td><td>--</td><td>--</td><td>--</td></tr><tr><td>--</td><td>--</td><td>--</td><td>--</td></tr><tr><td>--</td><td>--</td><td>--</td><td>--</td></tr></table>				Load Current [A]	Input Power [W]			Input Volt. 18[V]	Input Volt. 24[V]	Input Volt. 36[V]	0.00	1.8	1.9	2.4	0.80	23.0	23.5	25.0	1.60	44.0	44.2	45.8	2.40	65.3	65.6	67.0	3.20	87.3	87.2	88.7	4.00	109.9	109.5	111.2	4.20	115.6	115.1	116.7	4.62	127.9	127.1	128.6	--	--	--	--	--	--	--	--	--	--	--	--
Load Current [A]	Input Power [W]																																																									
	Input Volt. 18[V]	Input Volt. 24[V]	Input Volt. 36[V]																																																							
0.00	1.8	1.9	2.4																																																							
0.80	23.0	23.5	25.0																																																							
1.60	44.0	44.2	45.8																																																							
2.40	65.3	65.6	67.0																																																							
3.20	87.3	87.2	88.7																																																							
4.00	109.9	109.5	111.2																																																							
4.20	115.6	115.1	116.7																																																							
4.62	127.9	127.1	128.6																																																							
--	--	--	--																																																							
--	--	--	--																																																							
--	--	--	--																																																							
Note: Slanted line shows the range of the rated load current.																																																										
(注) 斜線は定格負荷電流範囲を示す。																																																										

COSEL

ModelCBS1002424		Temperature25℃																															
Item	Efficiency (by Input Voltage) 効率（入力電圧特性）	Testing Circuitry	Figure A																														
Object																																	
1. Graph		2. Values																															
<div><div>---□--- Load 50%</div><div>—△— Load 100%</div></div> <table><thead><tr><th>Input Voltage [V]</th><th>Load 50% Efficiency [%]</th><th>Load 100% Efficiency [%]</th></tr></thead><tbody><tr><td>16</td><td>87.0</td><td>85.9</td></tr><tr><td>18</td><td>87.3</td><td>86.6</td></tr><tr><td>20</td><td>87.3</td><td>86.8</td></tr><tr><td>24</td><td>87.0</td><td>86.9</td></tr><tr><td>30</td><td>86.1</td><td>86.4</td></tr><tr><td>36</td><td>85.1</td><td>85.7</td></tr><tr><td>40</td><td>84.1</td><td>85.0</td></tr><tr><td>--</td><td>--</td><td>--</td></tr><tr><td>--</td><td>--</td><td>--</td></tr></tbody></table> <p>Note: Slanted line shows the range of the rated input voltage.</p> <p>(注) 斜線は定格入力電圧範囲を示す。</p>		Input Voltage [V]	Load 50% Efficiency [%]	Load 100% Efficiency [%]	16	87.0	85.9	18	87.3	86.6	20	87.3	86.8	24	87.0	86.9	30	86.1	86.4	36	85.1	85.7	40	84.1	85.0	--	--	--	--	--	--		
Input Voltage [V]	Load 50% Efficiency [%]	Load 100% Efficiency [%]																															
16	87.0	85.9																															
18	87.3	86.6																															
20	87.3	86.8																															
24	87.0	86.9																															
30	86.1	86.4																															
36	85.1	85.7																															
40	84.1	85.0																															
--	--	--																															
--	--	--																															

COSEL

Model		CBS1002424		Temperature		25℃	
Item		Efficiency (by Load Current) 効率 (負荷特性)		Testing Circuitry		Figure A	
Object							
1. Graph				2. Values			

△

Input Volt. 18V

□

Input Volt. 24V


○

Input Volt. 36V

Efficiency [%]

</

COSEL

Model	CBS1002424																																																	
Item	Load Regulation 静的負荷変動	Temperature	25℃																																															
Object	+24V4.2A	Testing Circuitry	Figure A																																															
1. Graph		2. Values																																																
<div><div><div>—△—</div><div>Input Volt. 18V</div></div><div><div>---□---</div><div>Input Volt. 24V</div></div><div><div>---○---</div><div>Input Volt. 36V</div></div></div>  <p>Output Voltage [V]</p> <p>Load Current [A]</p> <p>Note: Slanted line shows the range of the rated load current.</p> <p>(注) 斜線は定格負荷電流範囲を示す。</p>		<table><tr><th rowspan="2">Load Current [A]</th><th colspan="3">Output Voltage [V]</th></tr><tr><th>Input Volt. 18[V]</th><th>Input Volt. 24[V]</th><th>Input Volt. 36[V]</th></tr><tr><td>0.0</td><td>23.892</td><td>23.892</td><td>23.893</td></tr><tr><td>0.8</td><td>23.892</td><td>23.893</td><td>23.893</td></tr><tr><td>1.6</td><td>23.892</td><td>23.893</td><td>23.893</td></tr><tr><td>2.4</td><td>23.892</td><td>23.893</td><td>23.893</td></tr><tr><td>3.2</td><td>23.893</td><td>23.893</td><td>23.893</td></tr><tr><td>4.0</td><td>23.893</td><td>23.893</td><td>23.894</td></tr><tr><td>4.2</td><td>23.893</td><td>23.893</td><td>23.894</td></tr><tr><td>4.6</td><td>23.893</td><td>23.893</td><td>23.894</td></tr><tr><td>--</td><td>--</td><td>--</td><td>--</td></tr><tr><td>--</td><td>--</td><td>--</td><td>--</td></tr></table>		Load Current [A]	Output Voltage [V]			Input Volt. 18[V]	Input Volt. 24[V]	Input Volt. 36[V]	0.0	23.892	23.892	23.893	0.8	23.892	23.893	23.893	1.6	23.892	23.893	23.893	2.4	23.892	23.893	23.893	3.2	23.893	23.893	23.893	4.0	23.893	23.893	23.894	4.2	23.893	23.893	23.894	4.6	23.893	23.893	23.894	--	--	--	--	--	--	--	--
Load Current [A]	Output Voltage [V]																																																	
	Input Volt. 18[V]	Input Volt. 24[V]	Input Volt. 36[V]																																															
0.0	23.892	23.892	23.893																																															
0.8	23.892	23.893	23.893																																															
1.6	23.892	23.893	23.893																																															
2.4	23.892	23.893	23.893																																															
3.2	23.893	23.893	23.893																																															
4.0	23.893	23.893	23.894																																															
4.2	23.893	23.893	23.894																																															
4.6	23.893	23.893	23.894																																															
--	--	--	--																																															
--	--	--	--																																															

COSEL

Model		CBS1002424		Temperature25℃ Testing CircuitryFigure A																																																																											
Item		Ripple Voltage (by Load Current) リップル電圧 (負荷特性)																																																																													
Object		+24V4.2A																																																																													
1. Graph				2. Values																																																																											
<div><div><div>—△—Input Volt. 18V</div><div>- - -○- - -Input Volt. 36V</div></div><div><table><thead><tr><th>Load Current [A]</th><th>18V Input [mV]</th><th>36V Input [mV]</th></tr></thead><tbody><tr><td>0.0</td><td>5</td><td>15</td></tr><tr><td>0.8</td><td>15</td><td>20</td></tr><tr><td>1.7</td><td>15</td><td>20</td></tr><tr><td>2.5</td><td>15</td><td>20</td></tr><tr><td>3.4</td><td>15</td><td>20</td></tr><tr><td>4.2</td><td>15</td><td>20</td></tr><tr><td>5.0</td><td>15</td><td>20</td></tr><tr><td>--</td><td>--</td><td>--</td></tr><tr><td>--</td><td>--</td><td>--</td></tr><tr><td>--</td><td>--</td><td>--</td></tr><tr><td>--</td><td>--</td><td>--</td></tr></tbody></table></div><div><p>Ripple Voltage is shown as p-p in the figure below.</p><p>Note: Slanted line shows the range of the rated load current.</p><p>リップル電圧は、下図 p - p 値で示される。</p><p>(注) 斜線は定格負荷電流範囲を示す。</p></div></div>				Load Current [A]	18V Input [mV]	36V Input [mV]	0.0	5	15	0.8	15	20	1.7	15	20	2.5	15	20	3.4	15	20	4.2	15	20	5.0	15	20	--	--	--	--	--	--	--	--	--	--	--	--	<table><thead><tr><th rowspan="2">Load Current [A]</th><th colspan="2">Ripple Voltage [mV]</th></tr><tr><th>Input Volt. 18 [V]</th><th>Input Volt. 36 [V]</th></tr></thead><tbody><tr><td>0.0</td><td>5</td><td>15</td></tr><tr><td>0.8</td><td>15</td><td>20</td></tr><tr><td>1.7</td><td>15</td><td>20</td></tr><tr><td>2.5</td><td>15</td><td>20</td></tr><tr><td>3.4</td><td>15</td><td>20</td></tr><tr><td>4.2</td><td>15</td><td>20</td></tr><tr><td>5.0</td><td>15</td><td>20</td></tr><tr><td>--</td><td>--</td><td>--</td></tr><tr><td>--</td><td>--</td><td>--</td></tr><tr><td>--</td><td>--</td><td>--</td></tr><tr><td>--</td><td>--</td><td>--</td></tr></tbody></table>		Load Current [A]	Ripple Voltage [mV]		Input Volt. 18 [V]	Input Volt. 36 [V]	0.0	5	15	0.8	15	20	1.7	15	20	2.5	15	20	3.4	15	20	4.2	15	20	5.0	15	20	--	--	--	--	--	--	--	--	--	--	--	--
Load Current [A]	18V Input [mV]	36V Input [mV]																																																																													
0.0	5	15																																																																													
0.8	15	20																																																																													
1.7	15	20																																																																													
2.5	15	20																																																																													
3.4	15	20																																																																													
4.2	15	20																																																																													
5.0	15	20																																																																													
--	--	--																																																																													
--	--	--																																																																													
--	--	--																																																																													
--	--	--																																																																													
Load Current [A]	Ripple Voltage [mV]																																																																														
	Input Volt. 18 [V]	Input Volt. 36 [V]																																																																													
0.0	5	15																																																																													
0.8	15	20																																																																													
1.7	15	20																																																																													
2.5	15	20																																																																													
3.4	15	20																																																																													
4.2	15	20																																																																													
5.0	15	20																																																																													
--	--	--																																																																													
--	--	--																																																																													
--	--	--																																																																													
--	--	--																																																																													
<div><div>Ripple [mVp-p]</div><div></div><div><p>Fig. Complex Ripple Wave Form</p><p>図 リップル波形詳細図</p></div></div>																																																																															

COSEL

ModelCBS1002424		Temperature25℃	
ItemRipple-Noise リップルノイズ		Testing CircuitryFigure A	
Object+24V4.2A			
1. Graph		2. Values	

—△— Input Volt. 18V

- -○- - Input Volt. 36V

Ripple-Noise is shown as p-p in the figure below.
Note: Slanted line shows the range of the rated load current.

リップルノイズは、下図 p - p 値で示される。
(注) 斜線は定格負荷電流範囲を示す。


Fig.Complex Ripple Noise Wave Form
図 リップルノイズ波形

Load Current [A]	Ripple-Noise [mV]	
	Input Volt. 18 [V]	Input Volt. 36 [V]
0.0	15	35
0.8	20	40
1.7	25	40
2.5	30	35
3.4	30	35
4.2	35	40
5.1	40	40
--	—	—
--	—	—
--	—	—
--	—	—

Model	CBS1002424
Item	Overcurrent Protection 過電流保護
Object	+24V4. 2A

Temperature	25°C
Testing Circuitry	Figure A

1. Graph



Note: Slanted line shows the range of the rated load current.

(注) 斜線は定格負荷電流範囲を示す。

Intermittent operation occurs when the output voltage is from 16.8V to 0V.

16.8V～0V間は、間欠モードとなる。

2. Values

[illegible]

COSEL

Model		CBS1002424	
Item		Overvoltage Protection 過電圧保護	
Object		+24V4.2A	
1. Graph		2. Values	

—△—

Input Volt.

18V

---□---

Input Volt.

24V

-○-

Input Volt.

36V

Operating Point [V]


<

COSEL

Model	CBS1002424	Temperature	25°C
Item	Dynamic Load Response 動的負荷変動	Testing Circuitry	Figure A
Object	+24V4.2A		

Input Volt. 24 V
Cycle 1000 ms

Load Current



Min. Load (0A) \longleftrightarrow

Load 100% (4.2A)

500 mV/div



500 μ s/div




5 ms/div


Min. Load (0A) \longleftrightarrow

Load 50% (2.1A)

500 mV/div



500 μ s/div




5 ms/div


Load 10% (0.42A) \longleftrightarrow

Load 100% (4.2A)

500 mV/div




500 μ s/div



5 ms/div

COSEL



COSEL

Model		CBS1002424	
Item		Ambient Temperature Drift 周囲温度変動	
Object		+24V4.2A	

1. Graph

—△—

Input Volt. 18V

---□---

Input Volt. 24V

---○---

Input Volt. 36V

Output Voltage [V]

COSEL

ModelCBS1002424

ItemMinimum Input Voltage for Regulated Output Voltage
最低レギュレーション電圧

Object+24V4.2A

1. Graph

---□---

Load 50%

—△—

Load 100%

Input Voltage [V]

</

COSEL

<

COSEL

COSEL

Model		CBS1002424	Testing Circuitry Figure A
Item		Output Voltage Accuracy 定電圧精度	
Object		+24V4.2A	

1. Output Voltage Accuracy

This is defined as the value of the output voltage, regulation load, ambient temperature and input voltage varied at random in the range as specified below.

Temperature : -40 ~ 100°C

Input Voltage : 18 ~ 36V

Load Current : 0 ~ 4.2A

* Output Voltage Accuracy = $\pm (\text{Maximum of Output Voltage} - \text{Minimum of Output Voltage}) / 2$

* Output Voltage Accuracy (Ration) = $\frac{\text{Output Voltage}}{\text{Rated Output Voltage}} \times 100$

1. 定電圧精度

周囲温度、入力電圧、負荷電流を下記仕様内で、任意に変動させたときの出力電圧の変動をいう。

周囲温度 : -40 ~ 100°C

入力電圧 : 18 ~ 36V

負荷電流 : 0 ~ 4.2A

* 定電圧精度(変動値) = $\pm (\text{出力電圧の最高値} - \text{出力電圧の最低値}) / 2$

* 定電圧精度(変動率) = $\frac{\text{変動値}}{\text{定格出力電圧}} \times 100$

2. Values

Item	Temperature [°C]	Input Voltage[V]	Output		Output Voltage Accuracy	
			Current[A]	Voltage[V]	Value [mV]	Ration [%]
Maximum Voltage	-40	36	4.2	23.959	±111	±0.5
Minimum Voltage	100	36	4.2	23.737		

		Testing Circuitry Figure A
Model	CBS1002424	
Item	Condense 結露特性	
Object	+24V4.2A	

1. Condensation test

Testing procedure is as follows.

- ① Keeping and cooling the unit in a tank at -10°C for an hour with the input off.
- ② Taking it out of the tank and dewing itself in a room where the temperature is 25°C and the humidity is 40%RH.
- ③ Testing electrical characteristics of the unit to confirm there be no fault.

1. 結露特性試験

入力を切った状態で、恒温槽で -10°C に冷却しておき、約1時間後に恒温槽から取り出し、室温 25°C 、湿度40%RHの状態におき結露させ、その電気的特性の測定を行い異常のないことを確認する。

2. Values

Item	Data	Testing Conditions
Output Voltage [V]	23.923	Input Volt. : 24V, Load Current. : 4.2A
Line Regulation [mV]	3	Input Volt. : 18~36V, Load Current. : 4.2A
Load Regulation [mV]	1	Input Volt. : 24V, Load Current. : 0~4.2A

COSEL

Model		CBS1002424	Temperature 25℃ Testing Circuitry Figure B
Item		Line Noise Tolerance 入力雑音耐量	
Object		+24V4.2A	

1. Conditions

- Input Voltage : 24 V
- Pulse Voltage : 2000 V
- Pulse Cycle : 16.7 mS
- Pulse Input Duration : 1 min. or more
- Load : 100 %

2. Results

Pulse Width [nS]	MODE		No protection failure should occur	DC-like Regulation of Output Voltage
		POLARITY	保護回路の誤動作がない	出力電圧の直流的変動
50	COMMON	+	OK	no fluctuation
		—	OK	no fluctuation
	NORMAL	+	OK	no fluctuation
		—	OK	no fluctuation
1000	COMMON	+	OK	no fluctuation
		—	OK	no fluctuation
	NORMAL	+	OK	no fluctuation
		—	OK	no fluctuation

COSEL

