

Temperature increase of main components

Model: MGW1R512□□

1. Conditions

- (1) Input :DC 12 [V]
 (2) Output :Rated output
 (3) Cooling method :Convection cooling
 (4) Mounting method :Shown as Fig.1.1

2. Result

Table 2.1 Temperature increase of main components

No.	Parts name	Symbol No.	Increase (ΔT)		Rated temp. [°C]	Reference
			[deg]			
			±12V	±15V		
1	Switching MOS-FET	TR11	15	16	150	Junction Temp.
2	Switching MOS-FET	TR101	15	17	150	Junction Temp.
3	Power control IC	IC11	15	15	150	Junction Temp.
4	Rectified diode (Output)	D201	17	18	150	Junction Temp.
5	Rectified diode (Output)	D202	17	19	150	Junction Temp.
6	Photocoupler	PC11	15	15	125	Junction Temp.
7	Transformer (PCB)	P2	16	17	130	
8	CASE	CASE	15	16	110	Top Surface Center
9						
10						
11						
12						
13						
14						
15						
16						
17						
18						
19						
20						




Fig.1.1 Mounting method