

TEST DATA OF MHFS61205

Regulated DC Power Supply
October 27, 2021

Approved by : _____ Kenichi Tsukada

Design Manager

Prepared by : _____ Yoshihiko Saeki

Design Engineer

COSEL CO.,LTD.




CONTENTS

1.Input Current (by Load Current)	1
2.Efficiency (by Load Current)	2
3.Line Regulation	3
4.Load Regulation	4
5.Ripple-Noise	4
6.Dynamic Load Response	5
7.Rise and Fall Time	6
8.Overcurrent Protection	7
9.Ambient Temperature Drift	8
10.Minimum Input Voltage for Regulated Output Voltage	8
11.Switching frequency (by Load Current)	9
12.Figure of Testing Circuitry	10

(Final Page 10)

COSEL

Model	MHFS61205
Item	Input Current (by Load Current)
Object	_____



Note: Slanted line shows the range of the rated load current.

Temperature 25°C
Testing Circuitry Figure A

2.Values

Load Current [A]	Input Current [A]				
	4.5[V]	5[V]	9[V]	12[V]	18[V]
0.00	0.039	0.036	0.008	0.008	0.008
0.24	0.348	0.315	0.182	0.144	0.116
0.48	0.662	0.595	0.337	0.261	0.190
0.72	0.996	0.891	0.492	0.375	0.268
0.96	1.344	1.199	0.652	0.492	0.344
1.08	1.524	1.358	0.734	0.553	0.382
1.20	*1	1.524	0.817	0.613	0.421
1.32	*1	1.690	0.900	0.674	0.460
--	-	-	-	-	-
--	-	-	-	-	-
--	-	-	-	-	-

*1 Maximum output current at 4.5V input Voltage is 80% of rated load current.
Refer to instruction manuals for details of input derating.

COSEL


Model	MHFS61205	Temperature Testing Circuitry	25°C Figure A																																																																													
Item	Efficiency (by Load Current)																																																																															
Object	<hr/>																																																																															
1.Graph	<p>Legend:</p> <ul style="list-style-type: none"> Input Volt. 4.5V Input Volt. 5V Input Volt. 9V Input Volt. 12V Input Volt. 18V <p>Efficiency [%]</p> <p>Load Current [A]</p>																																																																															
	<p>2.Values</p> <table border="1"> <thead> <tr> <th rowspan="2">Load Current [A]</th> <th colspan="5">Efficiency [%]</th> </tr> <tr> <th>4.5[V]</th> <th>5[V]</th> <th>9[V]</th> <th>12[V]</th> <th>18[V]</th> </tr> </thead> <tbody> <tr><td>0.00</td><td>-</td><td>-</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>0.24</td><td>77.7</td><td>77.5</td><td>74.4</td><td>70.4</td><td>58.3</td></tr> <tr><td>0.48</td><td>81.7</td><td>81.8</td><td>80.2</td><td>77.6</td><td>71.0</td></tr> <tr><td>0.72</td><td>81.5</td><td>82.0</td><td>82.3</td><td>81.0</td><td>75.6</td></tr> <tr><td>0.96</td><td>80.3</td><td>81.1</td><td>82.8</td><td>82.3</td><td>78.7</td></tr> <tr><td>1.08</td><td>79.6</td><td>80.5</td><td>82.8</td><td>82.6</td><td>79.5</td></tr> <tr><td>1.20</td><td>*1</td><td>79.8</td><td>82.7</td><td>82.7</td><td>80.3</td></tr> <tr><td>1.32</td><td>*1</td><td>79.1</td><td>82.5</td><td>82.7</td><td>80.7</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>--</td><td>-</td><td>-</td><td>-</td><td>-</td><td>-</td></tr> </tbody> </table>			Load Current [A]	Efficiency [%]					4.5[V]	5[V]	9[V]	12[V]	18[V]	0.00	-	-	-	-	-	0.24	77.7	77.5	74.4	70.4	58.3	0.48	81.7	81.8	80.2	77.6	71.0	0.72	81.5	82.0	82.3	81.0	75.6	0.96	80.3	81.1	82.8	82.3	78.7	1.08	79.6	80.5	82.8	82.6	79.5	1.20	*1	79.8	82.7	82.7	80.3	1.32	*1	79.1	82.5	82.7	80.7	--	-	-	-	-	-	--	-	-	-	-	-	--	-	-	-	-	-
Load Current [A]	Efficiency [%]																																																																															
	4.5[V]	5[V]	9[V]	12[V]	18[V]																																																																											
0.00	-	-	-	-	-																																																																											
0.24	77.7	77.5	74.4	70.4	58.3																																																																											
0.48	81.7	81.8	80.2	77.6	71.0																																																																											
0.72	81.5	82.0	82.3	81.0	75.6																																																																											
0.96	80.3	81.1	82.8	82.3	78.7																																																																											
1.08	79.6	80.5	82.8	82.6	79.5																																																																											
1.20	*1	79.8	82.7	82.7	80.3																																																																											
1.32	*1	79.1	82.5	82.7	80.7																																																																											
--	-	-	-	-	-																																																																											
--	-	-	-	-	-																																																																											
--	-	-	-	-	-																																																																											
	<p>Note: Slanted line shows the range of the rated load current.</p> <p>*1 Maximum output current at 4.5V input Voltage is 80% of rated load current. Refer to instruction manuals for details of input derating.</p>																																																																															

COSEL

Model	MHFS61205
Item	Line Regulation
Object	+5V1.2A

Temperature 25°C
Testing Circuitry Figure A

1. Graph




Note: Slanted line shows the range of the rated input voltage.

2. Values

Input Voltage [V]	Output Voltage [V]	
	Load 50%	Load 100%
4.3	5.054	*1
4.5	5.054	*1
5.0	5.054	5.056
7.5	5.054	5.056
9.0	5.054	5.056
12.0	5.054	5.056
15.0	5.054	5.056
18.0	5.055	5.056
20.0	5.055	5.056


*1 Maximum output current at 4.5V input
Voltage is 80% of rated load current.
Refer to instruction manuals for details of
input derating.

COSEL

 Temperature 25°C
 Testing Circuitry Figure A

2.Values

Load Current [A]	Output Voltage [V]				
	4.5[V]	5[V]	9[V]	12[V]	18[V]
0.00	5.062	5.062	5.062	5.061	5.061
0.24	5.061	5.061	5.060	5.060	5.060
0.48	5.060	5.060	5.059	5.059	5.058
0.72	5.059	5.059	5.058	5.058	5.057
0.96	5.058	5.058	5.057	5.057	5.056
1.08	5.057	5.057	5.057	5.056	5.056
1.20	*1	5.057	5.056	5.056	5.056
1.32	*1	5.056	5.056	5.056	5.055
--	-	-	-	-	-
--	-	-	-	-	-
--	-	-	-	-	-



*1 Maximum output current at 4.5V input Voltage is 80% of rated load current.
 Refer to instruction manuals for details of input derating.


 Temperature 25°C
 Testing Circuitry Figure B

COSEL

Model		MHFS61205	Temperature Testing Circuitry	25°C Figure A
Item		Dynamic Load Response		
Object		+5V1.2A		

Input Volt. 12 V Response. $t_1=t_2=50\mu\text{s}$. Typ
 Cycle 100 ms




COSEL

Model	MHFS61205
Item	Rise and Fall Time
Object	+5V1.2A


Temperature 25°C
Testing Circuitry Figure A

1. Graph




2. Values

Load	Time	T_d	T_r	T_s	T_h	T_f	[ms]
50 %		0.3	0.7	1.0	0.1	0.5	
100 %		0.3	0.7	1.0	0.1	0.2	



COSEL

Model	MHFS61205
Item	Overcurrent Protection
Object	+5V1.2A


 Temperature 25°C
 Testing Circuitry Figure A

2.Values

Output Voltage [V]	Load Current [A]				
	4.5[V]	5[V]	9[V]	12[V]	18[V]
4.75	1.429	1.470	1.649	1.648	1.596
4.50	1.371	1.401	1.684	1.679	1.625
4.00	1.574	1.614	1.757	1.745	1.684
3.50	1.678	1.709	1.836	1.814	1.744
3.00	1.772	1.805	1.920	1.887	1.806
2.50	1.898	1.926	2.009	1.963	1.869
2.00	2.023	2.070	2.111	2.034	1.900
1.50	2.156	2.185	2.202	2.118	1.961
1.00	2.243	2.298	2.289	2.189	2.017
0.50	2.313	2.323	2.254	2.196	2.044
0.00	2.382	2.373	2.209	2.118	1.925
--	-	-	-	-	-

Note: Slanted line shows the range of the rated load current.

Maximum output current at 4.5V input Voltage is 80% of rated load current.
 Refer to instruction manuals for details of input derating.



Model	MHFS61205	
Item	Ambient Temperature Drift	Testing Circuitry Figure A
Object	+5V1.2A	

1.Values

Load 100%

Ambient Temperature[°C]	Output Voltage [V]				
	Input Volt. 4.5V*1	Input Volt. 5V	Input Volt. 9V	Input Volt. 12V	Input Volt. 18V
-40	5.035	5.036	5.037	5.037	5.037
25	5.052	5.053	5.054	5.054	5.054
50	5.059	5.058	5.059	5.059	5.059

*1 Load 80%

Item	Minimum Input Voltage for Regulated Output Voltage	Testing Circuitry Figure A
Object	+5V1.2A	

1.Values

Ambient Temperature[°C]	Input Voltage [V]	
	Load 50%	Load 80%
-40	3.5	3.7
25	3.6	3.5
50	3.5	3.6

COSEL

Model	MHFS61205	Temperature	25°C																																																																													
Item	Switching frequency (by Load Current)	Testing Circuitry	Figure A																																																																													
Object	+5V1.2A																																																																															
1.Graph																																																																																
2.Values	<table border="1"> <thead> <tr> <th rowspan="2">Load Current [A]</th> <th colspan="5">Switching Frequency [kHz]</th> </tr> <tr> <th>4.5[V]</th> <th>5[V]</th> <th>9[V]</th> <th>12[V]</th> <th>18[V]</th> </tr> </thead> <tbody> <tr> <td>0.00</td> <td>1202</td> <td>1255</td> <td>1265</td> <td>1265</td> <td>1250</td> </tr> <tr> <td>0.24</td> <td>627</td> <td>670</td> <td>879</td> <td>940</td> <td>992</td> </tr> <tr> <td>0.48</td> <td>418</td> <td>453</td> <td>642</td> <td>705</td> <td>780</td> </tr> <tr> <td>0.72</td> <td>309</td> <td>340</td> <td>516</td> <td>571</td> <td>646</td> </tr> <tr> <td>0.96</td> <td>242</td> <td>269</td> <td>420</td> <td>480</td> <td>550</td> </tr> <tr> <td>1.08</td> <td>217</td> <td>243</td> <td>386</td> <td>445</td> <td>513</td> </tr> <tr> <td>1.20</td> <td>*1</td> <td>221</td> <td>358</td> <td>414</td> <td>479</td> </tr> <tr> <td>1.32</td> <td>*1</td> <td>203</td> <td>333</td> <td>388</td> <td>451</td> </tr> <tr> <td>--</td> <td>-</td> <td>-</td> <td>-</td> <td>-</td> <td>-</td> </tr> <tr> <td>--</td> <td>-</td> <td>-</td> <td>-</td> <td>-</td> <td>-</td> </tr> <tr> <td>--</td> <td>-</td> <td>-</td> <td>-</td> <td>-</td> <td>-</td> </tr> </tbody> </table>			Load Current [A]	Switching Frequency [kHz]					4.5[V]	5[V]	9[V]	12[V]	18[V]	0.00	1202	1255	1265	1265	1250	0.24	627	670	879	940	992	0.48	418	453	642	705	780	0.72	309	340	516	571	646	0.96	242	269	420	480	550	1.08	217	243	386	445	513	1.20	*1	221	358	414	479	1.32	*1	203	333	388	451	--	-	-	-	-	-	--	-	-	-	-	-	--	-	-	-	-	-
Load Current [A]	Switching Frequency [kHz]																																																																															
	4.5[V]	5[V]	9[V]	12[V]	18[V]																																																																											
0.00	1202	1255	1265	1265	1250																																																																											
0.24	627	670	879	940	992																																																																											
0.48	418	453	642	705	780																																																																											
0.72	309	340	516	571	646																																																																											
0.96	242	269	420	480	550																																																																											
1.08	217	243	386	445	513																																																																											
1.20	*1	221	358	414	479																																																																											
1.32	*1	203	333	388	451																																																																											
--	-	-	-	-	-																																																																											
--	-	-	-	-	-																																																																											
--	-	-	-	-	-																																																																											
Note:	Slanted line shows the range of the rated load current.																																																																															
	When load current is low, MH operates intermittently, so switching frequency would not become constant.																																																																															
	<p>*1 Maximum output current at 4.5V input Voltage is 80% of rated load current. Refer to instruction manuals for details of input derating.</p>																																																																															

COSEL




Figure A

Data Acquisition/Control Unit




Figure B