

ABNORMAL TEST RESULT

OF MODEL RMC30U-1/RMC30A-1

1. Did Cheese Cloth or Paper Glow?

No.

2. Did Ground Fuse Open?

No.

3. Dielectric breakdown?

No.

4. Other Results?

See the following pages .

(Abnormal Test Result: 6-1 ~ 6-12)

There was no emission of flame, molten metal, ignition of cheesecloth, dielectric breakdown, opening of the ground fuse, other indication of a shock or fire hazard.

8. Abnormal Test [アブノーマル試験] : Bull.1402C, cl 5.5

Rated Input Current: 0.95, Rated Output Voltage: AVR1: 5V
AVR2: 12V
AVR3: -12V

No.	Component [部品番号]	S/C[短絡] or OPEN [開放]	Gnd Fuse Open [接地ヒューズ断]	Flame or Glowing [赤熱または溶融]	Input Curr- ent	Output Volta- ge	Comment [コメント]
1	C11	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Fil Open Hi pot OK
2			<input type="checkbox"/> Yes[有] <input type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input type="checkbox"/> No[無]			
3	C13	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Fil Open Hi pot OK
4	C14	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
5	C15	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0.65	AVR1: 4.97 AVR2: 12 AVR3: -12	Hi pot OK
6	C16	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0.59	AVR1: 4.69 AVR2: 12 AVR3: -12	Hi pot OK
7	C17	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0.59	AVR1: 5 AVR2: 12 AVR3: -12	R21, R22 Open Hi pot OK
8	C51	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0.09	AVR1: 0 AVR2: 0 AVR3: 0	OCP operate Hi pot OK
9	C52	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0.09	AVR1: 0 AVR2: 0 AVR3: 0	OCP operate Hi pot OK
10	C53	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0.09	AVR1: 0 AVR2: 0 AVR3: 0	OCP operate Hi pot OK
11	C54	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0.09	AVR1: 0 AVR2: 0 AVR3: 0	OCP operate Hi pot OK
12	C55	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change

Compliance [判定] : ☒ Yes [合] / ☐ No [否]

※ OVP: Over Voltage Protection

OCP: Over Current Protection

8. Abnormal Test [アブノーマル試験]: Bull.1402C, cl 5.5

AVR1: 5V

AVR2: 12V

Rated Input Current: 0.95 A, Rated Output Voltage: AVR3: -12V

No.	Component [部品番号]	S/C[短絡] or OPEN [開放]	Gnd Fuse Open [接地ヒューズ断]	Flame or Glowing [赤熱または溶融]	Input Curr- ent	Output Volta- ge	Comment [コメント]
1	C56	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.51	AVR1: 4.32 AVR2: 11.4 AVR3: 11.8	Hi pot OK
2	C57	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.05	AVR1: 0 AVR2: 0 AVR3: 0	OCP operate Hi pot OK
3	C58	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.05	AVR1: 0 AVR2: 0 AVR3: 0	OCP operate Hi pot OK
4	C59	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.55	AVR1: 5 AVR2: 0 AVR3: -12	AVR2 OCP operate Hi pot OK
5	C60	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.06	AVR1: 0 AVR2: 0 AVR3: 0	OCP operate Hi pot OK
6	C61	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.54	AVR1: 5 AVR2: 12 AVR3: 0	AVR3 OCP operate Hi pot OK
7	C62	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
8	D11	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
9	D12	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.48	AVR1: 4.05 AVR2: 10.7 AVR3: -10.8	Hi pot OK
10	D13	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 4.99 AVR2: 12 AVR3: -12	Hi pot OK
11	D14	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
12	D15	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK

Compliance [判定]: ☒ Yes [合] / ☐ No [否]

* OVP: Over Voltage Protection

OCP: Over Current Protection

8. Abnormal Test [アブノーマル試験] : Bull.1402C, cl 5.5

AVR1: 5V

AVR2: 12V

Rated Input Current: 0.95 A, Rated Output Voltage: AVR3: -12V

No.	Component [部品番号]	S/C[短絡] or OPEN [開放]	Gnd Fuse Open - [接地ヒューズ断]	Flame or Glowing [赤熱または溶融]	Input Curr- ent	Output Volta- ge	Comment [コメント]
1	DS1	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.03	AVR1: 0 AVR2: 0 AVR3: 0	OCP operate Hi pot OK
2	DS2	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.55	AVR1: 5 AVR2: 0 AVR3: -12	AVR2 OCP operate Hi pot OK
3	DS3	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.03	AVR1: 0 AVR2: 0 AVR3: 0	OCP operate Hi pot OK
4	DS4	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.54	AVR1: 5 AVR2: 12 AVR3: 0	AVR3 OCP operate Hi pot OK
5	IC51 (K-A)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.09	AVR1: 1.25 AVR2: 3.56 AVR3: -2.92	Hi pot OK
6	IC51 (K-R)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.04	AVR1: 3.64 AVR2: 9.67 AVR3: -9.73	Hi pot OK
7	IC51 (R-A)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.84	AVR1: 6.15 AVR2: 12 AVR3: -12	Hi pot OK
8	IC52 (I-D)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.84	AVR1: 5 AVR2: 13.7 AVR3: -12	Hi pot OK
9	IC52 (D-G)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.55	AVR1: 5 AVR2: 0 AVR3: -12	AVR2 OCP operate Hi pot OK
10	IC52 (I-G)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.05	AVR1: 0 AVR2: 0 AVR3: 0	OCP operate Hi pot OK
11	IC53 (I-D)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.78	AVR1: 5 AVR2: 12 AVR3: -14.7	Hi pot OK
12	IC53 (D-G)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.54	AVR1: 5 AVR2: 12 AVR3: 0	AVR3 OCP operate Hi pot OK



Compliance [判定] : ☒ Yes [合] / ☐ No [否]

* OVP : Over Voltage Protection

OCP : Over Current Protection

8. Abnormal Test [アブノーマル試験] : Bull.1402C, cl 5.5

Rated Input Current: 0.95 A, Rated Output Voltage: AVR1: 5V
AVR2: 12V
AVR3: -12V

No.	Component [部品番号]	S/C[短絡] or OPEN [開放]	Gnd Fuse Open - [接地ヒューズ断]	Flame or Glowing [赤熱または溶融]	Input Curr- ent	Output Volta- ge	Comment [コメント]
1	IC52 (I-G)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.06	AVR1: 0 AVR2: 0 AVR3: 0	OCP operate Hi pot OK
2	L11 	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Fil Open Hi pot OK
3	L11 	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
4	L51	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
5	LED51 (K-A)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
6	PC11 LED (A-K)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
7	PC11 detector (A-K)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
8	PC11 detector (G-K)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
9	PC11 detector (A-G)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
10	PC12 LED (A-K)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.84	AVR1: 6.08 AVR2: 12 AVR3: -12	Hi pot OK
11	PC12 detector (C-E)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
12	SS11	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Fil Open Hi pot OK

Compliance [判定] : ☒ Yes [合] / ☐ No [否]

* OVP : Over Voltage Protection

OCP : Over Current Protection

8. Abnomal Test [アブノーマル試験] : Bull.1402C, cl 5.5

Rated Input Current: 0.95 A, Rated Output Voltage: AVR1: 5V
AVR2: 12V
AVR3: -12V

No.	Component [部品番号]	S/C[短絡] or OPEN [開放]	Gnd Fuse Open [接地ヒューズ断]	Flame or Glowing [赤熱または溶融]	Input Curr- ent	Output Volta- ge	Comment [コメント]
1	SS51	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.09	AVR1: 0 AVR2: 0 AVR3: 0	OCP operate Hi pot OK
2	T11 (2-3)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
3	T11 (4-5)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
4	T11 (6-7)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
5	T11 (7-8)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
6	T11 (9-10)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
7	TR11 (C-E)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
8	TR11 (C-B)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
9	TR11 (B-E)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
10	TR12 (C-E)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
11	TR12 (C-B)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
12	TR12 (B-E)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	OVP operate Hi pot OK

Compliance [判定] : ☒ Yes [合] / ☐ No [否]

* OVP : Over Voltage Protection

OCP : Over Current Protection

8. Abnormal Test [アブノーマル試験] : Bull.1402C,cl 5.5

Rated Input Current: 0.95 A , Rated Output Voltage: AVR1: 5V
AVR2: 12V
AVR3: -12V

No.	Component [部品番号]	S/C[短絡] or OPEN [開放]	Gnd Fuse Open [接地ヒューズ断]	Flame or Glowing [赤熱または溶融]	Input Curr- ent	Output Volta- ge	Comment [コメント]
1	TR13 (C-E)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Flt Open ZD11, D11 short Hi pot OK
2	TR13 (C-B)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Flt Open ZD11 short TR13 short Hi pot OK
3	TR13 (B-E)	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
4	ZD11	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
5	ZD12	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.35	AVR1: 3.38 AVR2: 9.01 AVR3: -8.96	Hi pot OK
6	ZD51	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
7	ZD52	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
8	ZD53	S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.05	AVR1: 0 AVR2: 0 AVR3: 0	OCP operate Hi pot OK
9		S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]		AVR1: AVR2: AVR3:	
10		S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]		AVR1: AVR2: AVR3:	
11		S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]		AVR1: AVR2: AVR3:	
12		S/C	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]		AVR1: AVR2: AVR3:	

Compliance [判定] : ☒ Yes [合] / ☐ No [否]

* OVP : Over Voltage Protection

OCP : Over Voltage Protection

8. Abnormal Test [アブノーマル試験] : Bull.1402C, cl 5.5

Rated Input Current: 0.95A, Rated Output Voltage: AVR1: 5V
AVR2: 12V
AVR3: -12V

No.	Component [部品番号]	S/C[短絡] or OPEN [開放]	Gnd Fuse Open [接地ヒューズ断]	Flame or Glowing [赤熱または溶融]	Input Curr- ent	Output Volta- ge	Comment [コメント]
1	C11	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
2		Open	<input type="checkbox"/> Yes[有] <input type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input type="checkbox"/> No [無]		AVR1: AVR2: AVR3:	
3	C13	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.79	AVR1: 3.23 AVR2: 8.7 AVR3: -8.9	Hi pot OK
4	C14	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
5	C15	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.13	AVR1: 1.73 AVR2: 4.79 AVR3: -4.3	Hi pot OK
6	C16	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
7	C17	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
8	C51	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
9	C52	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
10	C53	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
11	C54	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
12	C55	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change

Compliance [判定] : ☒ Yes [合] / ☐ No [否]

* OVP: Over Voltage Protection

OCP: Over Current Protection

8. Abnormal Test [アブノーマル試験] : Bull.1402C, cl 5.5

Rated Input Current: 0.95A , Rated Output Voltage: AVR1: 5V
AVR2: 12V
AVR3: -12V

No.	Component [部品番号]	S/C[短絡] or OPEN [開放]	Gnd Fuse Open [接地ヒューズ断]	Flame or Glowing [赤熱または溶融]	Input Curr- ent	Output Volta- ge	Comment [コメント]
1	C56	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 4.99 AVR2: 12 AVR3: -12	Hi pot OK
2	C57	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
3	C58	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
4	C59	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
5	C60	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -11.9	Hi pot OK
6	C61	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -10.5	Hi pot OK
7	C62	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
8	D11	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
9	D12	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	OVP operate Hi pot OK
10	D13	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
11	D14	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.59	AVR1: 4.7 AVR2: 12 AVR3: -12	Hi pot OK
12	D15	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change

Compliance [判定] : ☒ Yes [合] / ☐ No [否]

* OVP: Over Voltage Protection

OCP: Over Current Protection

8. Abnormal Test [アブノーマル試験]: Bull.1402C, cl 5.5

Rated Input Current: 0.95A, Rated Output Voltage: AVR1: 5V
AVR2: 12V
AVR3: -12V

No.	Component [部品番号]	S/C[短絡] or OPEN [開放]	Gnd Fuse Open - [接地ヒューズ断]	Flame or Glowing [赤熱または溶融]	Input Curr- ent	Output Volta- ge	Comment [コメント]
1	D51	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.42	AVR1: 5 AVR2: 0 AVR3: -12	Hi pot OK
2	D52	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
3	D53	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.59	AVR1: 5 AVR2: 12 AVR3: 0	Hi pot OK
4	D54	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
5	IC51 (K,A)	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.84	AVR1: 6.15 AVR2: 12 AVR3: -12	Hi pot OK
6	IC51 (R)	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.84	AVR1: 6.15 AVR2: 12 AVR3: -12	Hi pot OK
7	IC52 (I)	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.42	AVR1: 5 AVR2: 0 AVR3: -12	Hi pot OK
8	IC52 (O)	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.42	AVR1: 5 AVR2: 0 AVR3: -12	Hi pot OK
9	IC52 (G)	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.43	AVR1: 5 AVR2: 0.5 AVR3: -12	Hi pot OK
10	IC53 I	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.59	AVR1: 5 AVR2: 12 AVR3: 0	Hi pot OK
11	IC53 (O)	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.59	AVR1: 5 AVR2: 12 AVR3: 0	Hi pot OK
12	IC53 (G)	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.62	AVR1: 5 AVR2: 12 AVR3: -9.95	Hi pot OK

Compliance [判定]: ☒ Yes [合] / ☐ No [否]

* OVP: Over Voltage Protection

OCP: Over Current Protection

8. Abnormal Test [アブノーマル試験] : Bull.1402C, cl 5.5

Rated Input Current: 0.95A , Rated Output Voltage: AVR1: 5V
AVR2: 12V
AVR3: -12V

No.	Component [部品番号]	S/C[短絡] or OPEN [開放]	Gnd Fuse Open [接地ヒューズ断]	Flame or Glowing [赤熱または溶融]	Input Curr- ent	Output Volta- ge	Comment [コメント]
1	L11	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
2	L51	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
3	LED51 (K,A)	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
4	PC11 LED (K,A)	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
5	PC11 detector (K,A)	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
6	PC11 detector (G)	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
7	PC12 LED (K,A)	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0.84	AVR1: 6.15 AVR2: 12 AVR3: -12	Hi pot OK
8	PC12 detector (C,E)	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
9	SS11	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
10	SS51	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Z053 short Hi pot OK
11	T11 Zor3	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
12	T11 4or5	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No[無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK

Compliance [判定] : ☒ Yes [合] / ☐ No [否]

* OVP: Over Voltage Protection

OCP: Over Current Protection

8. Abnormal Test [アブノーマル試験]: Bull.1402C, cl 5.5

Rated Input Current: 0.95 A, Rated Output Voltage: AVR1: 5V
AVR2: 12V
AVR3: -12V

No.	Component [部品番号]	S/C[短絡] or OPEN [開放]	Gnd Fuse Open - [接地ヒューズ断]	Flame or Glowing [赤熱または溶融]	Input Curr- ent	Output Volta- ge	Comment [コメント]
1	T11 9or10	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	2D53 short Hi pot OK
2	T11 8	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.42	AVR1: 5 AVR2: 0 AVR3: -12	Hi pot OK
3	T11 6	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.59	AVR1: 5 AVR2: 12 AVR3: 0	Hi pot OK
4	T11 7	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.48	AVR1: 5 AVR2: 3.20 AVR3: 11.9	Hi pot OK
5	TR11 (C, E)	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
6	TR11 (B)	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
7	TR12 (C, E)	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	OVP operate Hi pot OK
8	TR12 (B)	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	OVP operate Hi pot OK
9	TR13 (C, E)	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
10	TR13 (B)	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
11	2D11	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
12	2D12	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change

Compliance [判定]: ☒ Yes [合] / ☐ No [否]

* OVP: Over Voltage Protection

OCP: Over Current Protection

8. Abnormal Test [アブノーマル試験] : Bull.1402C, cl 5.5

Rated Input Current: 0.95A, Rated Output Voltage: AVR1: 5V
AVR2: 12V
AVR3: -12V

No.	Component [部品番号]	S/C[短絡] or OPEN [開放]	Gnd Fuse Open [接地ヒューズ断]	Flame or Glowing [赤熱または溶融]	Input Curr- ent	Output Volta- ge	Comment [コメント]
1	ZD51	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
2	ZD52	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
3	ZD53	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0.67	AVR1: 5 AVR2: 12 AVR3: -12	Nothing change
4	TH11	Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	0	AVR1: 0 AVR2: 0 AVR3: 0	Hi pot OK
5		Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]		AVR1: AVR2: AVR3:	
6		Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]		AVR1: AVR2: AVR3:	
7		Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]		AVR1: AVR2: AVR3:	
8		Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]		AVR1: AVR2: AVR3:	
9		Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]		AVR1: AVR2: AVR3:	
10		Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]		AVR1: AVR2: AVR3:	
11		Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]		AVR1: AVR2: AVR3:	
12		Open	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]	<input type="checkbox"/> Yes[有] <input checked="" type="checkbox"/> No [無]		AVR1: AVR2: AVR3:	

Compliance [判定] : ☒ Yes [合] / ☐ No [否]

* OVP : Over Voltage Protection

OCP : Over Current Protection