

## ABNORMAL TEST RESULT

OF MODEL SNDHS100B

1. Did Cheese Cloth or Paper Glow?

No.

2. Did Ground Fuse Open?

No.

3. Dielectric breakdown?

No.

4. Other Results?

See the following pages .

( FMEA : 2/3 ~ 3/3)

( Abnormal Test Result: - )

There was no emission of flame, molten metal, ignition of cheesecloth, dielectric breakdown, opening of the ground fuse, other indication of a shock or fire hazard.

F M E A

Component	Mode		Comment	Output Voltage (V)
C11	Open		Normal operation.	
	Short		F11 opened, No hazard.	AVR1:0
C12	Open		Normal operation.	
	Short		F11 opened, No hazard.	AVR1:0
C51	Open	except12,15,24	Normal operation.	
	Short	except12,15,24	No hazard.	AVR1:0
C52	Open		Normal operation.	
	Short		No hazard.	AVR1:0
C53	Open		Normal operation.	
	Short		No hazard.	AVR1:0
C56	Open		Normal operation.	
	Short		No hazard.	AVR1:0
D11	Open		No hazard.	AVR1:0
	Short		Normal operation.	
L11	Open		No hazard.	AVR1:0
	Short		Normal operation.	
PC12	Open	A,K	No hazard.	AVR1:0
		C,E	No hazard.	AVR1:0
	Short	A-K	No hazard.	AVR1:0
		C-E	Normal operation.	
PS1	Open	+Vin	No hazard.	AVR1:0
		RC	No hazard.	AVR1:0
		-Vin	No hazard.	AVR1:0
		+Vout	No hazard.	AVR1:0
		TRM	Normal operation.	
		-Vout	No hazard.	AVR1:0

F M E A

[illegible]