

## ABNORMAL TEST RESULT

OF MODEL SNDPG750

1. Did Cheese Cloth or Paper Glow?

No.

2. Did Ground Fuse Open?

No.

3. Dielectric breakdown?

No.

4. Other Results?

See the following pages .

( FMEA : 2/3 ~ 3/3 )  
( Abnormal Test Result: - )

There was no emission of flame, molten metal, ignition of cheesecloth, dielectric breakdown, opening of the ground fuse, other indication of a shock or fire hazard.

## F M E A

Component	Mode		Comment	Output Voltage (V)
C11	Open		Normal operation.	
	Short		F11 opened, No hazard.	AVR1:0
C12	Open		Normal operation.	
	Short		F11 opened, No hazard.	AVR1:0
C13	Open		Normal operation.	
	Short		F11 opened, No hazard.	AVR1:0
C14	Open		Normal operation.	
	Short		F11 opened, No hazard.	AVR1:0
C53	Open		Normal operation.	
	Short		F11 opened, No hazard.	AVR1:0
C54	Open		Normal operation.	
	Short		F11 opened, No hazard.	AVR1:0
C55	Open		Normal operation.	
	Short		F11 opened, No hazard.	AVR1:0
C56	Open		Normal operation.	
	Short		F11 opened, No hazard.	AVR1:0
C57	Open		Normal operation.	
	Short		F11 opened, No hazard.	AVR1:0
L11	Open		No hazard.	AVR1:0
	Short		Normal operation.	
L12	Open		No hazard.	AVR1:0
	Short		Normal operation.	
PS1	Open	AC1(L)	No hazard.	AVR1:0
		AC2(N)	No hazard.	AVR1:0
		R	Normal operation.	
		+Vout	R51 opened, No hazard.	AVR1:0

## F M E A

Component	Mode		Comment	Output Voltage (V)
PS1	Open	-Vout	No hazard.	AVR1:0
		AUX	Normal operation.	
		ENA	Normal operation.	
	Short	AC1(L) - AC2(N)	F11 opened, No hazard.	AVR1:0
		R +Vout	Normal operation.	
		+Vout - -Vout	F11 opened, No hazard.	AVR1:0
		AUX -ENA	Normal operation.	
SK11	Open		Normal operation.	
	Short		Normal operation.	
SK12	Open		Normal operation.	
	Short		Normal operation.	
TR31	Open	E	Normal operation.	
		C	Normal operation.	
		B	Normal operation.	
	Short	E -C	Normal operation.	
		C -B	Normal operation.	
		B -E	Normal operation.	
J21	Open		Normal operation.	
R11	Open		Normal operation.	
R12	Open		Normal operation.	
R13	Open		Normal operation.	
R14	Open		Normal operation.	
R31	Open		Normal operation.	
R32	Open		Normal operation.	
R51	Open		Normal operation.	