

**COSEL**

**TEST DATA OF ZTS1R54812  
(48.0V INPUT)**

Regulated DC Power Supply

Date : Mar. 5. 1998

Approved by : N. Shiraishi  
Design Manager

Prepared by : T. Tsuru  
Design Engineer

**コーセル株式会社  
COSEL CO., LTD.**

CONTENTS

1. Line Regulation	1
静的入力変動	
2. Efficiency	2
効率	
3. Load Regulation	3
静的負荷変動	
4. Ripple Voltage (by Load Current)	4
リップル電圧(負荷電流特性)	
5. Ripple-Noise	5
リップルノイズ	
6. Overcurrent Protection	6
過電流保護	
7. Dynamic Load Responce	7
動的負荷変動	
8. Rise and Fall Time	8
立ち上り、立下がり時間	
9. Ambient Temperature Drift	9
周囲温度変動	
10. Minimum Input Voltage for Regulated Output Voltage	10
最低レギュレーション電圧	
11. Ripple Voltage (by Ambient Temperature)	11
リップル電圧(周囲温度特性)	
12. Time Lapse Drift	12
経時ドリフト	
13. Output Voltage Accuracy	13
定電圧精度	
14. Condensation	14
結露特性	
15. Figure of Testing Circuitry	15
測定回路図	

(Final Page 15 )

**COSEL**


Model	ZTSIR54812	Temperature Testing Circuitry 25°C Figure A																																									
Item	Line Regulation 静的入力変動																																										
Object	+12V 0.13A																																										
1. Graph	<p style="text-align: center;">-----□----- Load 50% -----△----- Load 100%</p>	2. Values																																									
		<table border="1"> <thead> <tr> <th rowspan="2">Input Voltage [V]</th> <th>Load 50%</th> <th>Load 100%</th> </tr> <tr> <th>Output Volt. [V]</th> <th>Output Volt. [V]</th> </tr> </thead> <tbody> <tr><td>33.0</td><td>12.077</td><td>12.076</td></tr> <tr><td>36.0</td><td>12.077</td><td>12.076</td></tr> <tr><td>42.0</td><td>12.077</td><td>12.075</td></tr> <tr><td>48.0</td><td>12.077</td><td>12.075</td></tr> <tr><td>54.0</td><td>12.077</td><td>12.075</td></tr> <tr><td>60.0</td><td>12.077</td><td>12.075</td></tr> <tr><td>66.0</td><td>12.077</td><td>12.075</td></tr> <tr><td>72.0</td><td>12.077</td><td>12.075</td></tr> <tr><td>75.0</td><td>12.076</td><td>12.075</td></tr> <tr><td>-</td><td>-</td><td>-</td></tr> <tr><td>-</td><td>-</td><td>-</td></tr> <tr><td>-</td><td>-</td><td>-</td></tr> </tbody> </table>	Input Voltage [V]	Load 50%	Load 100%	Output Volt. [V]	Output Volt. [V]	33.0	12.077	12.076	36.0	12.077	12.076	42.0	12.077	12.075	48.0	12.077	12.075	54.0	12.077	12.075	60.0	12.077	12.075	66.0	12.077	12.075	72.0	12.077	12.075	75.0	12.076	12.075	-	-	-	-	-	-	-	-	-
Input Voltage [V]	Load 50%	Load 100%																																									
	Output Volt. [V]	Output Volt. [V]																																									
33.0	12.077	12.076																																									
36.0	12.077	12.076																																									
42.0	12.077	12.075																																									
48.0	12.077	12.075																																									
54.0	12.077	12.075																																									
60.0	12.077	12.075																																									
66.0	12.077	12.075																																									
72.0	12.077	12.075																																									
75.0	12.076	12.075																																									
-	-	-																																									
-	-	-																																									
-	-	-																																									

Note: Slanted line shows the range of the rated input voltage.

(注)斜線は定格入力電圧範囲を示す。

**COSEL**

Model	ZTS1R54812
Item	Efficiency 効率
Object	—



Note: Slanted line shows the range of the rated input voltage.

(注)斜線は定格入力電圧範囲を示す。


Temperature 25°C  
Testing Circuitry Figure A

2. Values

Input Voltage [V]	Load 50%	Load 100%
	Efficiency [%]	Efficiency [%]
33.0	71.2	75.1
36.0	70.5	75.3
42.0	68.0	74.9
48.0	65.3	73.9
54.0	62.2	72.6
60.0	59.2	70.9
66.0	56.1	69.0
72.0	53.3	67.0
75.0	51.8	66.1
—	—	—
—	—	—
—	—	—

**COSEL**

Model	ZTS1R54812
Item	Load Regulation 靜的負荷変動
Object	+12V 0.13A



Note: Slanted line shows the range of the rated load current.

(注)斜線は定格負荷電流範囲を示す。


Temperature 25°C  
Testing Circuitry Figure A

2. Values

Load Current [A]	Input Volt.	Input Volt.	Input Volt.
	36.0[V]	48.0[V]	72.0[V]
Output	Output	Output	Output
Volt. [V]	Volt. [V]	Volt. [V]	Volt. [V]
0.00	12.078	12.078	12.078
0.02	12.076	12.077	12.077
0.04	12.076	12.076	12.076
0.06	12.076	12.076	12.076
0.08	12.076	12.076	12.076
0.10	12.076	12.076	12.076
0.12	12.075	12.076	12.076
0.13	12.075	12.076	12.075
0.14	12.075	12.075	12.075
-	-	-	-

**COSEL**

Model	ZTS1R54812
Item	Ripple Voltage (by Load Current) リップル電圧(負荷電流特性)
Object	+12V 0.13A

Temperature  
Testing Circuitry      25°C  
Figure A

## 2. Values

Load Current [A]	Input Volt. 36.0 [V]	Input Volt. 72.0 [V]
	Ripple Output Volt. [mV]	Ripple Output Volt. [mV]
0.00	8	10
0.02	8	10
0.04	8	10
0.06	8	10
0.08	8	10
0.10	10	10
0.12	10	10
0.13	10	10
0.14	15	15
—	—	—
—	—	—

Ripple Voltage is shown as p-p in the figure below.

Note: Slanted line shows the range of the rated load current.

リップル電圧は、下図 p - p 値で示される。

(注)斜線は定格負荷電流範囲を示す。

T1: Due to AC Input Line  
入力商用周期

T2: Due to Switching  
スイッチング周期




Fig. Complex Ripple Wave Form  
図 リップル波形詳細図

**COSEL**


Model	ZTS1R54812	Temperature Testing Circuitry	25°C Figure A																																				
Item	Ripple-Noise リップルノイズ																																						
Object	+12V 0.13A																																						
1. Graph		2. Values																																					
<p>[mV]</p>		<table border="1"> <thead> <tr> <th>Load current [A]</th> <th>Input Volt. 36.0 [V] Ripple-Noise [mV]</th> <th>Input Volt. 72.0 [V] Ripple-Noise [mV]</th> </tr> </thead> <tbody> <tr><td>0.00</td><td>10</td><td>10</td></tr> <tr><td>0.02</td><td>15</td><td>15</td></tr> <tr><td>0.04</td><td>15</td><td>20</td></tr> <tr><td>0.06</td><td>15</td><td>20</td></tr> <tr><td>0.08</td><td>15</td><td>20</td></tr> <tr><td>0.10</td><td>20</td><td>20</td></tr> <tr><td>0.12</td><td>20</td><td>25</td></tr> <tr><td>0.13</td><td>25</td><td>25</td></tr> <tr><td>0.14</td><td>25</td><td>30</td></tr> <tr><td>—</td><td>—</td><td>—</td></tr> <tr><td>—</td><td>—</td><td>—</td></tr> </tbody> </table>		Load current [A]	Input Volt. 36.0 [V] Ripple-Noise [mV]	Input Volt. 72.0 [V] Ripple-Noise [mV]	0.00	10	10	0.02	15	15	0.04	15	20	0.06	15	20	0.08	15	20	0.10	20	20	0.12	20	25	0.13	25	25	0.14	25	30	—	—	—	—	—	—
Load current [A]	Input Volt. 36.0 [V] Ripple-Noise [mV]	Input Volt. 72.0 [V] Ripple-Noise [mV]																																					
0.00	10	10																																					
0.02	15	15																																					
0.04	15	20																																					
0.06	15	20																																					
0.08	15	20																																					
0.10	20	20																																					
0.12	20	25																																					
0.13	25	25																																					
0.14	25	30																																					
—	—	—																																					
—	—	—																																					
<p>Ripple-Noise is shown as p-p in the figure below. Note: Slanted line shows the range of the rated load current.</p> <p>リップルノイズは、下図 p - p 値で示される。 (注) 斜線は定格負荷電流範囲を示す。</p>			<p>T1: Due to AC Input Line T2: Due to Switching</p>																																				
<p>Fig. Complex Ripple Wave Form 図 リップル波形詳細図</p>			<p>BC-3116</p>																																				

**COSEL**

Model ZTS1R54812

Item Overcurrent Protection  
過電流保護

Object +12V 0.13A



Note: Slanted line shows the range of the rated load current.

(注)斜線は定格負荷電流範囲を示す。

Temperature 25°C  
Testing Circuitry Figure A

## 2. Values

Output Voltage [V]	Input Volt. 36.0[V]	Input Volt. 48.0[V]	Input Volt. 72.0[V]
	Load Current [A]	Load Current [A]	Load Current [A]
12.00	0.17	0.18	0.17
11.40	0.17	0.18	0.17
10.80	0.17	0.18	0.17
9.60	0.17	0.17	0.16
8.40	0.16	0.16	0.15
7.20	0.16	0.16	0.15
6.00	0.15	0.15	0.14
4.80	0.14	0.14	0.13
3.60	0.14	0.13	0.13
2.40	0.14	0.14	0.13
1.20	0.13	0.15	0.14
0.00	0.17	0.21	0.22

**COSEL**

Model	ZTS1R54812	Temperature Testing Circuitry Figure A
Item	Dynamic Load Response 動的負荷變動	
Object	+12V 0.13A	


Input Volt. 48.0 V

Cycle 100 mS


Load Current

Min. Load ←→  
Load 100 %


100 mV/div

Min. Load ←→  
Load 50 %

100 mV/div

Load 50%←→  
Load 100 %

100 mV/div



1 mS/div

**COSEL**


Model ZTS1R54812

Item Rise and Fall Time 立上り、立下り時間

Object +12V0.13A

Temperature 25°C  
Testing Circuitry Figure A


## 1. Graph



## 2. Values

Load \ Time	T d	T r	T s	T h	T f
50 %	0.75	2.55	3.30	7.25	5.00
100 %	0.75	2.55	3.30	3.00	5.20

[mS]




**COSEL**

Model ZTS1R54812

Item Ambient Temperature Drift  
周囲温度変動

Object +12V 0.13A

1. Graph



Note: Slanted line shows the range of the rated ambient temperature.

(注) 斜線は定格周囲温度範囲を示す。

Testing Circuitry Figure A

2. Values

Temperature [°C]	Input Volt. 36.0[V]	Input Volt. 48.0[V]	Input Volt. 72.0[V]
	Output Volt. [V]	Output Volt. [V]	Output Volt. [V]
-30	12.076	12.076	12.076
-20	12.076	12.076	12.076
-10	12.075	12.075	12.075
0	12.074	12.074	12.074
10	12.073	12.073	12.073
25	12.074	12.074	12.074
30	12.076	12.076	12.075
40	12.074	12.074	12.074
55	12.067	12.067	12.067
60	12.062	12.062	12.062
—	—	—	—

COSEL


Model ZTS1R54812

Item Minimum Input Voltage for Regulated Output Voltage  
最低レギュレーション電圧

Object +12V 0.13A

1. Graph

Load 50%  
[V] Load 100%



Note: Slanted line shows the range of the rated ambient temperature.

(注) 斜線は定格周囲温度範囲を示す。

Testing Circuitry Figure A

2. Values

Ambient Temp. [°C]	Load 50%	Load 100%
	Input Volt. [V]	Input Volt. [V]
-30	13.7	20.2
-20	13.7	20.2
-10	13.2	19.7
0	13.2	20.2
10	12.7	20.2
25	12.7	20.7
30	12.7	21.2
40	12.7	21.2
55	12.7	22.2
60	12.7	22.2
—	—	—


**COSEL**

Model ZTS1R54812

Item Ripple Voltage (by Ambient Temp.)  
リップル電圧 (周囲温度特性)

Object +12V 0.13A

## 1. Graph



Input Volt. 36.0 V

Note: Slanted line shows the range of the rated ambient temperature.

(注)斜線は定格周囲温度範囲を示す。

Testing Circuitry Figure A

## 2. Values


Ambient Temp. [°C]	Load 50%	Load 100%
	Ripple Output Volt. [mV]	Ripple Output Volt. [mV]
-30	10	15
-20	10	15
-10	10	15
0	8	15
10	8	10
20	8	10
30	8	10
40	5	10
50	5	10
60	5	10
—	—	—

**COSEL**

Model	ZTS1R54812
Item	Time Lapse Drift 経時ドリフト
Object	+12V 0.13A

Temperature 25 °C  
 Testing Circuitry Figure A

## 1. Graph



## 2. Values

Time since start [H]	Output Voltage [V]
0.0	12.078
0.5	12.074
1.0	12.074
2.0	12.074
3.0	12.074
4.0	12.074
5.0	12.074
6.0	12.074
7.0	12.074
8.0	12.074

**COSEL**

Model	ZTS1R54812	Testing Circuitry Figure A
Item	Output Voltage Accuracy 定電圧精度	
Object	+12V 0.13A	

**Output Voltage Accuracy**

This is defined as the value of the output voltage, regulation load, ambient temperature and input voltage varied at random in the range as specified below.

Temperature : -20~55 °C

Input Voltage : 36.0~72.0 V

Load Current : 0.00~0.13 A

$$* \text{ Output Voltage Accuracy} = \pm (\text{Maximum of Output Voltage} - \text{Minimum of Output Voltage}) / 2$$

$$* \text{ Output Voltage Accuracy (Ratio)} = \frac{\text{Voltage Accuracy}}{\text{Rated Output Voltage}} \times 100$$

**定電圧精度**

周囲温度、入力電圧、負荷を下記仕様内で、任意に変動させたときの出力電圧の変動をいう。

周囲温度 -20~55 °C

入力電圧 36.0~72.0 V

負荷電流 0.00~0.13 A

$$* \text{ 定電圧精度(変動値)} = \pm (\text{出力電圧の最高値} - \text{出力電圧の最低値}) / 2$$

$$* \text{ 定電圧精度(変動率)} = \frac{\text{変動値}}{\text{定格出力電圧}} \times 100$$

Item	Temperature [°C]	Input Voltage [V]	Output Current [A]	Output Voltage [V]	Output Voltage Accuracy [mV]	Output Voltage Accuracy(Ratio) [%]
Maximum Voltage	-20	72.0	0.00	12.079		
Minimum Voltage	55	72.0	0.13	12.064	±8	±0.1



Model	ZTS1R54812		
Item	Condensation 結露特性	Testing Circuitry	Figure A
Object	+12V 0.13A		

### 1. Condensation test

Testing procedure is as follows.

- ① Keeping and cooling the unit in a tank at -10°C for an hour with the input off.
- ② Taking it out of the tank and dewing itself in a room where the temperature is 25°C and the humidity is 40%RH.
- ③ Testing electrical characteristics of the unit to confirm there be no fault.

### 1. 結露特性試験

入力を切った状態で、恒温槽で-10°Cに冷却しておき、約1時間後に恒温槽から取り出し、室温25°C、湿度40%RHの状態におき結露させ、その電気的特性の測定を行い、異常のないことを確認する。

### 2. Values

Item	Data	Testing Conditions
Output Voltage [V]	11.913	Input Volt.: 48V, Load Current:0.13A
Line Regulation [mV]	1	Input Volt.: 36~72V, Load Current:0.13A
Load Regulation [mV]	4	Input Volt.: 48V, Load Current:0~0.13A




Figure A