参考資料

CO\$EL

immunity test

(3) Testing circuitry Fig.1

## MGFS3 series Reliability test results

Jan 31, 2017 OS DESIGN DEPT.

Jakarfuhi Jahano Takaruki Fukuda Approved a ĩ

			Prepared : Takaaki Sekiguchi Takaaki Sekiguchi		
No.	Test Item	Testing conditions	Conditions of acceptability	Number of samples	Number o failures
1	Heat cycle test	<ul> <li>(1) -40° C ~ 125° C 30minutes each</li> <li>(2) 800cycles</li> </ul>	<ul> <li>(1)No degradation of electric characteristics after test.</li> <li>(2)No crack at solder joint.</li> </ul>	5	0
2	High temperature/ High humidity bias test	<ul> <li>(1) Ta=85°C, RH=85%</li> <li>(2) Input Max.Voltege</li> <li>(3) Load 0%</li> <li>(4) 1000hours</li> </ul>	(1)No degradation of electric characteristics after test.	5	0
3	Vibration test	<ul> <li>(1) f=10~55Hz, 98.0m/s<sup>2</sup>(10G)</li> <li>(2) 3minutes period</li> <li>(3) 60minutes each X, Y and Z axis</li> </ul>	<ul> <li>(1)No degradation of electric characteristics after test.</li> <li>(2)No crack at solder joint.</li> <li>(3)No mechanical damage of appearance.</li> </ul>	6	0
4	Impact test	<ul> <li>(1) 490.3m/s<sup>2</sup>(50G), 11ms</li> <li>(2) Once each X, Y and Z axis</li> </ul>	<ul> <li>(1)No degradation of electric characteristics after test.</li> <li>(2)No crack at solder joint.</li> <li>(3)No thermal damage of appearance.</li> </ul>	3	0
5	Soldering heat test	<ul> <li>(1) Soldering iron 340~360°C,</li> <li>7.5 seconds</li> <li>(2) Mounting board : t=1.6mm / FR4</li> </ul>	(1)No crack at solder joint. (2)No marked damage of appearance.	1	0
6	Pin solder ability test	<ul> <li>(1) Pre-process</li> <li>Step1 Humidifying processing (100°C, 100%, 1H)</li> <li>Step2 Dip into flux</li> <li>(2) Dip soldering 230~240°C, 2sec</li> </ul>	(1)Over 95% of dipped part is covered with solder.	3	0
7	Pin strength test	<ul> <li>(1) Weight : 1kg</li> <li>(2) Bending angle : 90 deg., total 180 deg.</li> <li>(3) 1 cycle</li> </ul>	(1)No crack at solder joint. (2)No mechanical damage of appearance.	1	0
8	Static electricity	<ul> <li>(1) Applied voltage ±4kV</li> <li>(2) At rated input and load</li> <li>(2) Trategraphic for 1</li> </ul>	(1)No protection circuit fail. (2)No output voltage drop due to control	1	0

(3)No any other function fail.

